

# **MCS®-51 UTILITIES USER'S GUIDE FOR DOS SYSTEMS**

Order Number: 122747-001

REV.	REVISION HISTORY	DATE	APPD.
-001	Original issue.	3/86	M.K.S.

Additional copies of this manual or other Intel literature may be obtained from:

Literature Department  
Intel Corporation  
3065 Bowers Avenue  
Santa Clara, CA 95051

Intel retains the right to make changes to these specifications at any time, without notice. Contact your local sales office to obtain the latest specifications before placing your order.

Intel Corporation makes no warranty of any kind with regard to this material, including, but not limited to, the implied warranties of merchantability and fitness for a particular purpose. Intel Corporation assumes no responsibility for any errors that may appear in this document. Intel Corporation makes no commitment to update nor to keep current the information contained in this document.

Intel Corporation assumes no responsibility for the use of any circuitry other than circuitry embodied in an Intel product. No other circuit patent licenses are implied.

Intel software products are copyrighted by and shall remain the property of Intel Corporation. Use, duplication or disclosure is subject to restrictions stated in Intel's software license, or as defined in ASPR 7-104.9(a)(9).

No part of this document may be copied or reproduced in any form or by any means without the prior written consent of Intel Corporation.

The following are trademarks of Intel Corporation and its affiliates and may only be used to identify Intel products:

Above	i <sub>m</sub>	iSBC	Plug-A-Bubble
BITBUS	iMDDX	iSBX	PROMPT
COMMPuter	iMMX	iSDM	Promware
CREDIT	Insite	iSXM	QueX
Data Pipeline	int <sub>l</sub>	KEPROM	QUEST
Genius	int <sub>l</sub> IBOS	Library Manager	Ripplemode
i	InteleVision	MCS	RMX/80
i <sup>+</sup>	int <sub>l</sub> igent Identifier	Megachassis	RUPI
i <sup>+</sup> ICE	int <sub>l</sub> igent Programming	MICROMAINFRAME	Seamless
ICE	Intell <sub>ec</sub>	MULTIBUS	SLD
iCEL	Intellink	MULTICHANNEL	UPI
iCS	iOSP	MULTIMODULE	VLSiCEL
iDBP	iPDS	ONCE	
iDIS	iPSC	OpenNET	
iLBX	iRMX	PC-BUBBLE	

This manual describes the RL51 linker and locator and the LIB51 librarian for program modules produced by MCS-51 language translators such as ASM51 and PL/M-51.

The RL51 and the LIB51 program operate on an Intel development system with an 8080 or 8085 processor. The configuration must include 64K of RAM, a console, and at least one diskette or hard disk drive.

## NOTE

In this manual, the term MCS-51 refers to all members of the MCS-51 family of microcomputers and to the software development tools for the MCS-51 family.

## Reader's Guide

The manual is organized into six chapters and five appendixes:

Chapter 1 discusses the advantages of modular programming and summarizes the process of modular programming with the MCS-51 development tools.

Chapter 2 reviews the mechanics of linkage and location for the RL51 program.

Chapter 3 gives the details on invoking the linker/locator.

Chapter 4 discusses the files and displays produced by the RL51 program, with examples.

Chapter 5 contains three examples of programs, with the link and locate steps for each program.

Chapter 6 describes the LIB51, the MCS-51 library manager and its usage.

Appendix A presents the syntax of the RL51 commands with brief definitions of the controls.

Appendix B lists the error messages and warnings displayed by RL51, with suggestions for corrective action.

Appendix C lists a summary of LIB51 commands.

Appendix D lists the error messages generated by LIB51, with suggestions for corrective action.

Appendix E contains hexadecimal-decimal conversion tables as a convenient reference.

## Related Publications

The following list provides the manual title and order number for all Intel software development tools that run on DOS systems. Note that some manuals have two formats and two order numbers. One version of the manual is provided in a binder. This version is not sold separately; it can only be purchased when purchasing a software product. The second version, which has a soft cover, is sold separately. Use the soft cover number when ordering a manual separately.

Manual Title	Binder	Soft Cover
<i>MCS®-51 Macro Assembler User's Guide for DOS Systems</i>	122753	122752
<i>PL/M-51 User's Guide for DOS Systems</i>	122742	122743
<i>MCS®-51 Family of Single-Chip Microcomputers User's Manual for DOS Systems</i>		121517
<i>MCS®-51 Macro Assembly Language Pocket Reference for DOS Systems</i>		122755
<i>MCS®-51 Utilities Pocket Reference for DOS Systems</i>		122750

## Notational Conventions

UPPERCASE	Characters shown in uppercase must be entered in the order shown. Enter the command words as shown, or use a system-defined abbreviation. You may enter the characters in uppercase or lowercase.
<i>italic</i>	Italic indicates a meta symbol that may be replaced with an item that fulfills the rules for that symbol. The actual symbol may be any of the following:
<i>directory-name</i>	Is that portion of a <i>pathname</i> that acts as a file locator by identifying the device and/or directory containing the <i>filename</i> .
<i>filename</i>	Is a valid name for the part of a <i>pathname</i> that names a file.
<i>system-id</i>	Is a generic label placed on sample listings where an operating system-dependent name would actually be printed.
Vx.y	Is a generic label placed on sample listings where the version number of the product that produced the listing would actually be printed.
[ ]	Brackets indicate optional arguments or parameters.
{ }	One and only one of the enclosed entries must be selected unless the field is also surrounded by brackets, in which case it is optional.
{ }...	At least one of the enclosed items must be selected unless the field is also surrounded by brackets, in which case it is optional. The items may be used in any order unless otherwise noted.
	The vertical bar separates options within brackets [ ] or braces { }.
...	Ellipses indicate that the preceding argument or parameter may be repeated.
[,...]	The preceding item may be repeated, but each repetition must be separated by a comma.

punctuation

Punctuation other than ellipses, braces, and brackets must be entered as shown. For example, the punctuation shown in the following command must be entered:

```
SUBMIT PLM86(PROGA, SRC, '9 SEPT 81')
```

input lines

In interactive examples, user input lines are printed in white on black to differentiate them from system output.

<cr>

Indicates a carriage return.

# Table of Contents

---

<b>Chapter 1</b>	<b>Page</b>
<b>Introduction</b>	
The Advantages of Modular Programming .....	1-1
Efficient Program Development .....	1-1
Multiple Use of Subprograms .....	1-1
Ease of Debugging and Modifying .....	1-1
MCS®-51 Modular Program Development Process .....	1-1
Segments, Modules, Libraries, and Programs .....	1-2
Entering and Editing Source Modules .....	1-3
Assembly and Compilation .....	1-3
Relocation and Linkage .....	1-3
ROM and PROM Versions .....	1-3
ICE™-51 In-Circuit Emulator .....	1-3
Keeping Track of Files .....	1-3
 <b>Chapter 2</b>	
<b>The Mechanics of Linkage and Location with RL51</b>	
Major Functions .....	2-1
Selecting Modules .....	2-1
Partial Segments .....	2-2
Combining Relocatable Segments .....	2-2
Allocating Memory for Segments .....	2-3
Overlaying Data Segments .....	2-4
Resolving External References .....	2-4
Binding Relocatable Addresses .....	2-5
 <b>Chapter 3</b>	
<b>Using the RL51 Program</b>	
Introduction .....	3-1
RL51 Command Format Summary .....	3-1
Invocation .....	3-2
Input List .....	3-2
Output File .....	3-3
Controls .....	3-4
Listing Controls .....	3-4
PRINT/NOPRINT .....	3-4
PAGEWIDTH .....	3-5
Listing Switches .....	3-5
IXREF/NOIXREF .....	3-5
Linking Controls .....	3-7
NAME .....	3-7

	Page
Linking Switches .....	3-7
Locating Controls .....	3-8
Allocation Sequence .....	3-8
Format Summary .....	3-9
Table of Locating Controls .....	3-9
Notes on Locating Controls .....	3-9
Configuration Controls .....	3-11
RAMSIZE .....	3-11
OVERLAY/NOOVERLAY Controls .....	3-11
OVERLAY .....	3-12
NOOVERLAY .....	3-12
OVERLAY (A > B) or (A]B) .....	3-12
OVERLAY (A > *, * > B) or (A]*, *]B) .....	3-12
Abbreviations for Command Words .....	3-14

## Chapter 4

### RL51 Outputs

Console Display .....	4-1
Listing File .....	4-1
Link Summary .....	4-1
Symbol Table .....	4-2
Inter-Module Cross-Reference Report (IXREF) .....	4-4
Error Messages .....	4-4
Absolute Object File .....	4-5

## Chapter 5

### Examples of Program Development

Using Multiple Modules .....	5-1
Using the Locating Controls .....	5-16
Using RL51 with PL/M-51 Modules .....	5-16

## Chapter 6

### LIB51 Librarian

Introduction .....	6-1
Invoking LIB51 .....	6-1
Noninteractive Mode .....	6-1
Interactive Mode .....	6-1
Character Set .....	6-1
LIB51 Commands .....	6-1
Command Entry .....	6-1
Command Descriptions .....	6-3
ADD .....	6-3



	<b>Page</b>
CREATE .....	6-4
DELETE .....	6-5
EXIT .....	6-6
EXTRACT .....	6-7
HELP .....	6-8
LIST .....	6-9
REPLACE .....	6-10

## **Appendix A**

### **Summary of RL51 Controls**

## **Appendix B**

### **RL51 Error Messages**

## **Appendix C**

### **LIB51 Command Summary**

## **Appendix D**

### **LIB51 Error Messages**

## **Appendix E**

### **Hexadecimal-Decimal Conversion Table**

## **Index**

## **Figures**

1-1	MCS®-51 Program Development Process .....	1-2
4-1	Link Summary .....	4-2
4-2	Symbol Table .....	4-3
4-3	IXREF Listing .....	4-5
5-1	SAMP1 Listing File .....	5-2
5-2	SAMP2 Listing File .....	5-6
5-3	SAMP3 Listing File .....	5-9
5-4	RL51 Output File .....	5-13
5-5	TEST01 Assembly Listing File .....	5-19
5-6	RL51 Listing File without PRECEDE .....	5-20
5-7	RL51 Listing File with PRECEDE .....	5-21
5-8	PL/M-51 Listing File of CHK_EQ .....	5-22
5-9	ASM51 Listing File of HLTICE .....	5-24
5-10	RL51 Listing File of CHK_EQ .....	5-26

	Page
<b>Tables</b>	
2-1 Address Spaces and Segment Types .....	2-4
3-1 Definitions of Common Terms .....	3-2
3-2 Listing Switches .....	3-6
3-3 Linking Switches .....	3-8
3-4 Locating Controls .....	3-9
6-1 LIB51 Commands .....	6-2
A-1 Definitions of Common Terms .....	A-1
A-2 Listing Controls and Switches .....	A-3
A-3 Linking Controls and Switches .....	A-4
A-4 Locating Controls .....	A-4
A-5 Configuration Control .....	A-4
A-6 Overlay Controls .....	A-5
A-7 Abbreviations for Command Words .....	A-5
C-1 LIB51 Commands .....	C-1
E-1 Hexadecimal-Decimal Conversion Table .....	E-1

## **The Advantages of Modular Programming**

Many programs are too long or complex to write as a single unit. Programming becomes much simpler when the code is divided into small functional units. Modular programs are usually easier to code, debug, and change than monolithic programs.

The modular approach to programming is similar to the design of hardware that contains numerous circuits. The device or program is logically divided into "black boxes" with specific inputs and outputs. Once the interfaces between the units have been defined, detailed design of each unit can proceed separately.

## **Efficient Program Development**

Programs can be developed more quickly with the modular approach because small subprograms are easier to understand, design, and test than large programs. With the module inputs and outputs defined, the programmer can supply the needed input and verify the correctness of the module by examining the output. The separate modules are then linked and located into one program module. Finally, the completed program is tested.

## **Multiple Use of Subprograms**

Code written for one program is often useful in others. Modular programming allows these sections to be saved for future use. Because the code is relocatable, saved modules can be linked to any program that fulfills their input and output requirements. With monolithic programming, such sections of code are buried inside the program and are not so available for use by other programs.


If you put your frequently-used subprograms into a library, RL51 will take care to load only those you need. Thus, you can save RAM and ROM without having to keep track of what is needed and what is not.

## **Ease of Debugging and Modifying**

Modular programs are generally easier to debug than monolithic programs. Because the modular interfaces are well-defined, problems can be isolated to specific modules. Once the faulty module has been identified, fixing the problem is considerably simpler. When a program must be modified, modular programming simplifies the job. You can link new or modified modules to the existing program with confidence that the rest of the program will not be changed.

## **MCS<sup>®</sup>-51 Modular Program Development Process**

This section is a brief review of the program development process using an MCS-51 language translator (e.g., the relocatable MCS-51 assembler or PL/M-51 compiler), linker/locator, code converter programs, PROM programmer, and ICE<sup>™</sup>-51 in-circuit emulator. The process is shown in figure 1-1.

Figure 1-1. MCS<sup>®</sup>-51 Program Development Process

## Segments, Modules, Libraries, and Programs

In the initial design stages, the tasks to be performed by the program are defined and then partitioned into subprograms. Here are brief introductions to the kinds of subprograms used with the MCS-51 assembler and linker/locator.

A segment is a unit of code or data memory. A segment may be relocatable or absolute. A relocatable segment in a module can be a complete segment or can be a "partial" segment to be combined with other partial segments from other modules. A relocatable segment has a name, type, and other attributes that allow the linker to combine it with other partial segments, if required, and to correctly locate the segment. An absolute segment has no name and cannot be combined with other segments. See Chapter 2 for more detail on partial segments.

A module contains one or more segments or partial segments. A module has a name assigned by the user. The module definitions determine the scope of local symbols. An object file contains one or more modules. You can add modules to a file by transferring the new modules from their individual files to another file.

A library is a file that contains one or more modules. A library file is internally marked as a library, so RL51 can easily identify it as such. RL51 selects, out of the modules in the library, only those previously referenced. Libraries are created using the LIB51 utility, which is described in detail in Chapter 6.

A program consists of a single absolute module, merging all absolute and relocatable segments from all input modules. The name of the output module produced by RL51 can be defined by the user or allowed to default to the name of the first input module.

## Entering and Editing Source Modules

After the design is completed, use the text editor on your system to code the modules into source files. The source modules are coded in assembly language or a high-level language such as PL/M-51. The editor may also be used to make corrections in the source code.

## Assembly and Compilation

The assembler (ASM51) and compiler (PL/M-51) translate the source code into relocatable object code, producing an object file. The ASM51 object file is relocatable when at least one input segment is relocatable; otherwise the object file is an absolute file. The PL/M-51 object file is always relocatable. The assembler and compiler also produce a listing file showing the results of the translation. When the ASM51 or PL/M-51 invocation contains the DEBUG control, the object file also receives the symbol table and other debug information for use in symbolic debugging of the program.

## Relocation and Linkage

After translation of all modules of the program, the linker/locator, RL51, processes the object module files. The RL51 program combines relocatable partial segments with the same name, then assigns absolute memory locations to all the relocatable segments. RL51 also resolves all references between modules, using the library files when they are necessary for this resolution. RL51 outputs an absolute object module file that contains the completed program, and a summary listing file showing the results of the link/locate process, including a memory map, symbol table, and, optionally, an inter-module cross-reference (IXREF) listing.

## ROM and PROM Versions

The absolute object module produced by RL51 can be loaded into members of the MCS-51 family of microcomputers. For ROM versions of the microcomputer, the program is masked into ROM during the manufacturing process. For PROM versions and versions with no on-chip CODE memory, a PROM programmer is used to load the absolute module into program memory accessible to the microcomputer for execution. Refer to the *MCS-51 Family of Single Chip Microcomputers User's Manual* for details on the versions of microcomputers available.

## ICE™-51 In-Circuit Emulator

The ICE-51 in-circuit emulator is used for software and hardware debugging and integration into the final product. The absolute object modules produced by RL51 can be loaded into the emulator's memory for execution. Refer to the ICE-51 manual listed in the preface for details.

## Keeping Track of Files

It is convenient to use the extensions of filenames to indicate the stage in the process represented by the contents of each file. Thus, source code files can use extensions like .SRC, .A51, or .P51 (indicating that the code is for input to ASM51 or PL/M-51). Object code files receive the extension .OBJ by default or the user can specify another extension. Executable files generally have no extension. Listing files

can use .LST, the default extension given by the translator. RL51 uses .M51 for the default listing file extension (in order not to destroy the ASM51 listing file with the .LST extension).

Library files customarily have the extension .LIB.

Use caution with the extension .TMP, as many utilities (including RL51 and LIB51) create temporary files with this extension. These utilities will delete your file if it has the same name and extension as the temporary files they create.

This chapter describes the operation of the RL51 program. Most of the process is transparent to the user; however, an understanding of the operation at the level presented here will help you to use the linking and locating controls in the RL51 invocation. More specific details on the allocating process appear in Chapter 3.

## Major Functions

The RL51 program performs the following major functions:

1. Selects modules (including library processing)
2. Combines relocatable partial segments of the same name into a single segment
3. Allocates memory for the combined segments resulting from the previous step, and for all other complete relocatable segments from the input modules
4. Overlays data segments
5. Resolves external symbol references between the input modules
6. Binds relocatable addresses to absolute addresses
7. Produces an absolute object file
8. Produces a listing file consisting of a link summary, a symbol table, and an IXREF report
9. Detects and lists errors found in the input modules or in the RL51 command invocation

Functions 1, 2, 3, 5, and 6 are described in the remainder of this chapter. Functions 7, 8, and 9 are discussed in Chapter 4; the RL51 command invocation and overlaying of data segments are described in Chapter 3.

## Selecting Modules

Input files are processed in the order they are specified in the invocation command.

The processing of an input file varies according to the content—that is, whether it is a library or non-library file. A non-library file may contain a concatenation of zero or more object modules. A library file contains zero or more object modules together with control information. A module in a non-library file is processed if it was explicitly listed in the module list, or if the module list was not specified at all (in other words, as if all modules were listed implicitly).

The processing of a library file is more complicated. If a module list was specified for the library file, then it is processed in the same manner as a non-library file. If a module list was not specified, then the library file is processed only if the previously processed modules contained at least one unresolved external. The library is scanned for modules containing public symbols that match as yet unresolved externals. Each such module is processed as if it were explicitly specified. The selection process continues until the modules in the library cannot satisfy any unresolved externals (including any externals encountered while processing modules from the library).

RL51 will report an error if the same module name is encountered more than once during the link process.

Take TRIGON.LIB as an (utterly fictitious) example. Assume it contains procedures called SINE, COSINE, TANGENT, ARCSINE, ARCCOS, ARCTAN, HYPERBOLIC\_SINE, and HYPERBOLIC\_COSINE.

When RL51 starts processing TRIGON.LIB, it has already made a first pass over all files that appear before it in the invocation line. If one of these contains a reference to the external SINE, and there is no public by that name, RL51 will assume that the procedure SINE from TRIGON.LIB is to be loaded. Otherwise, it will leave SINE alone for the moment.

If, while loading from TRIGON.LIB, RL51 encounters new externals that a module in the library can resolve, it will scan the library once more. Thus, there is no logical order among modules in a library; they are all equal. If TANGENT calls SINE and COSINE, and they are in the same library, in any order whatsoever, a reference to TANGENT will cause all three to be loaded.

## Partial Segments

A segment is a unit of code memory or data memory. The portion of a segment defined in one module is called a partial segment. A partial segment has the following attributes (defined in the source module):

- **Name.** A relocatable segment has a name by which it is linked with other portions of the same segment from other modules. Absolute segments do not have names.
- **Type.** The type identifies the address space to which a segment belongs: CODE, XDATA, DATA, IDATA, or BIT.
- **Relocatability.** For relocatable segments only, this attribute describes any special constraints on relocation (PAGE, INPAGE, BLOCK, BITADDRESSABLE, or UNIT).
- **Size.** The size of the segment in bytes or bits, depending on the type.
- **Base Address.** The lowest address in the partial segment. For absolute segments, the base address is assigned at assembly time; for relocatable segments, it is assigned at location time.

Absolute segments are complete segments; they are taken as is into the output module. Relocatable segments are either defined by ASM51 users (using the SEGMENT directive in the source module) or automatically generated by the PL/M-51 compiler.

Refer to the *MCS-51 Macro Assembler User's Guide* for details on the assembler directives.

## Combining Relocatable Segments

After processing the invocation command, RL51 performs a first pass over the input modules identified in the command. Pass 1 generates a segment table, a public table, and an unresolved externals table. The segment table is discussed in this section; the other two tables are discussed later in this chapter.

The segment table contains the name, length, type, and relocation attribute of all combined segments from all modules. Combined segments are produced from the partial segments in the input modules according to the following rules:

- RL51 combines all partial segments with the same name into one relocatable segment. For example, if three input modules each have a partial relocatable segment named STACK, the segment table will have one segment named STACK that combines the length of the three partial segments.



- All the partial segments to be combined must be of the same type (CODE, DATA, IDATA, XDATA, or BIT). If any partial segments have the same names but different types, an error occurs.
- The length of the combined segment must not exceed the physical size of the memory type. Details on maximum size appear later in this chapter.
- The relocation attributes of all the partial segments to be combined must either be the same or UNIT-aligned combined with one other attribute. The combined segment receives the relocation attribute shared by the input partial segments, or, if the segments have attribute UNIT-aligned combined with one other attribute, the combined segment receives the more restrictive attribute.

For example, if the three partial segments named STACK have relocation attributes UNIT, PAGE, and UNIT, the combined segment has attribute PAGE (i.e., page-aligned). Note that the relocation attribute is applied to the combined segment, not to each component segment. To continue the example, since the relocation is PAGE, the combined segment will start on a page boundary, but the component segments will be packed together without any gaps.

## Allocating Memory for Segments

After the segment table is complete, RL51 can locate the segments within the memory spaces. Table 2-1 shows the address spaces used by MCS-51 processors, and the corresponding segment types.

The allocation process has a definite sequence; the exact order is presented in Chapter 3. As an overview, the process follows a general pattern of rules as follows:

1. Each of the types of memory space is allocated independent of the other spaces.
2. Within each space, absolute segments are allocated first, then segments specified within locating controls in the RL51 command, then other relocatable segments.
3. Because the on-chip data space represents three overlapping address spaces (DATA, IDATA, and BIT), the general pattern in rule 2 is modified.
  - a. Absolute BIT, DATA, and IDATA segments, and register banks are allocated first.
  - b. Segments specified in PRECEDE and BIT controls are allocated next, then other relocatable BIT (and BIT-ADDRESSABLE) segments (following rule 2).
  - c. DATA type segments are allocated next: segments in the DATA control first, then other relocatable DATA segments.
  - d. IDATA type segments (except ?STACK) are allocated next; segments in the IDATA control first, then other relocatable IDATA segments.
  - e. Segments specified in the STACK control are allocated, at as low an address as possible, provided that it is *above* all BIT, DATA, and IDATA segments allocated under (c) and (d).
  - f. Last, the segment ?STACK, if it exists and is IDATA, and is not mentioned in an explicit location control, is now allocated, at as low an address as possible, provided that it is *above* all BIT, DATA, and IDATA segments allocated under (c) and (d) and (e).

In most cases, you do not need to use any explicit controls to obtain a satisfactory allocation of segments. RL51 tries to fit your segments into the designated memory spaces as best it can following the rules. As you can see, most of the complexity occurs in the on-chip data space.

Table 2-1. Address Spaces and Segment Types

Memory Space	Maximum Size	Addresses	Segment Type
Code	64K bytes	0000H - 0FFFFH	CODE
External data	64K bytes	0000H - 0FFFFH	XDATA
On-chip data (direct addressing)	128 bytes	00H - 7FH	DATA
On-chip data (indirect addressing)	256 bytes (see 1)	00H - 0FFH	IDATA
Bit space in on-chip data memory	128 bits (see 2)	00H - 7FH	BIT

1. The amount of indirectly addressable on-chip data memory is machine-dependent within the MCS-51 microcomputer family (see the discussion of RAMSIZE control in Chapter 3).
2. This bit space overlaps byte addresses 20H - 2FH in on-chip data memory.

Note: Addresses in the special function register memory (direct data addresses 80H - 0FFH, bit addresses 80H - 0FFH) cannot be relocated; they are always absolute. Thus, these addresses are not referenced in this table.

Rule (f) applies to PL/M-51. PL/M-51 produces for the stack an IDATA segment called ?STACK, whose size is 1. Although, by applying rule (f), RL51 makes the stack as big as possible, it is the user responsibility to ensure that the size of the stack is large enough (the segment map shows where the stack is located).

No rules for the allocation process can guarantee an optimal solution. If you are short of memory and RL51's first try is not satisfactory, you can place the segments in memory using the locating controls. Details on the locating controls are given in Chapter 3.

## Overlaying Data Segments

On-chip RAM is a scarce resource on the MCS-51. To economize, the PL/M-51 compiler overlays data segments in the compiled module. RL-51 completes the work by overlaying the data segments across modules. This is accomplished by using the OVERLAY control. If RL-51 informed you about ignored segments due to lack of on-chip RAM, try this control. The use of OVERLAY is, in general, straightforward. However, for complex applications (for example, those with mixed ASM-51 and PL/M-51 modules), consult Chapter 3.

## Resolving External References

An external reference points to a location in another module. The EXTERNAL declaration for symbols tells RL51 that the reference is to a location defined in another module. In the latter module, the symbol is declared PUBLIC so that external references to that symbol in other modules can be satisfied.

As it processes the input modules, RL51 builds a table of public symbols and unresolved external references. As each public symbol is added to the table, any external references to that symbol are deleted. After all segments have been located,

the public symbols are bound to absolute addresses. RL51 issues a warning for any unresolved externals that remain in the table.

External symbols and corresponding public symbols must be compatible. That is, both must be defined to address the same address space, or at least one must be defined as a typeless symbol (NUMBER); and if the symbol represents a PL/M-51 procedure name, then both must share the same register bank (i.e., must be declared within the PL/M-51 source modules with the same USING attribute).

### **Binding Relocatable Addresses**

After allocating memory for the combined segments and binding the public symbols, RL51 makes a second pass (pass 2) through the input modules to build the listing file and fixup (i.e., bind to absolute addresses) any relocatable or external references. At this point, RL51 also processes debug records if requested, and performs fixups to any relocatable debug symbols that require processing to compute their absolute addresses.

## Introduction

The RL51 program performs two functions for MCS-51 programs:

- The link function, combining a number of object modules specified in an input list into a single object module in an output file
- The locate function, assigning absolute addresses to any relocatable addresses in the input modules

This chapter explains how to enter commands, how to continue a long command onto more than one input line, how to enter comments in the invocation, and how to use abbreviations of the command words.

The chapter then presents a summary of the format of the RL51 invocation command, followed by details on the elements of the command with examples.

## RL51 Command Format Summary

Here is a summary of the syntax of the RL51 invocation command. Refer to the Preface for an explanation of the command format notation.

The RL51 command has the overall format:

```
[ directory|device ] RL51 input-list [ TO output-file ] [ control-list ]
```

where

<i>directory device</i>	is the directory or device where RL51 resides.
<i>input-list</i>	is a list of filenames separated by commas. The files named in <i>input-list</i> should contain the relocatable modules to be linked and located in the final absolute output module. For each file, you can additionally specify which modules are to be included.
<i>output-file</i>	is the name of the file that is to receive the output module. If you omit this entry, the program will supply a default name based on the first filename in the input list.
<i>control-list</i>	selects options for listing, linking, and locating the output. The listing controls specify what information is to be sent to the listing file, and the page width to be used. The linking controls specify the name of the output module, and determine what debug information is to be placed in the output file. The locating controls allow you to assign absolute addresses to relocatable segments, and to specify the order of relocatable segments within a given type of memory. The configuration control is used to describe the actual configuration the object is aimed to. The overlay control overlays -data segments between modules.

The next several sections give details and examples of the elements of the RL51 command. Table 3-1 gives brief definitions of some of the terms used in the controls. A list of abbreviations for command words appears at the end of the chapter.

Table 3-1. Definitions of Common Terms

Term	Definition
<i>name</i>	Names can be from 1 to 40 characters in length and must be composed of letters A - Z, digits 0 - 9, or special characters (? , @ , _). The first character must be a letter or a special character.
<i>module-name</i>	Same as name.
<i>segment-name</i>	Same as name.
<i>pathname</i>	A valid filename reference or device reference. See next two items for examples.
<i>filename</i>	A reference to a disk file.
<i>device</i>	A reference to a non-disk device. Examples: :LP:, :CO:, :TO:
<i>value</i>	A 16-bit unsigned integer. Examples: 1011B, 304Q, 4096D (or just 4096), 0C300H
<i>address</i>	Same as value.

## Invocation

The RL51 command is a standard operating system invocation. Terminate the command with the RETURN key. Note that the termination carriage return is not shown in the command format notation.

You can continue the invocation line on one or more additional lines by entering the ampersand (&) before you enter the line terminator. The next line then automatically appears with the continuation prompt. Comments can also be entered on the invocation line by placing the comments after the ampersand or semicolon (;) because the compiler ignores all characters that appear after the ampersand or semicolon but before the carriage return/line feed that terminates the line.

Refer to your DOS user's guide for information on submitting batch file commands.

## Input List

The input list tells RL51 what files are to be processed. The files must be disk files containing relocatable object modules as described in Chapter 2.

The entry for each file in the list can include the following information:

- The directory or device. If the directory or device is omitted, the default directory or device is assumed.
- The filename. The filename is the name of the object file including an extension if one exists.
- A list of modules enclosed in parentheses. If a module list is provided, only the modules in the list are linked into the output file, and modules not in the list are ignored. If no module list is provided, the default for a non-library file is to link all modules in the file into the output module. The default for a library file is to link only those modules that satisfy previously declared external symbols (see the exact process in Chapter 2 under "Selecting Modules").

If a module named in the module list is not present in the file, the system issues an error message but does not halt the link process.

Module names (specified explicitly or implicitly) must be unique throughout the entire application.

## Examples

Following are examples of the RL51 input list—

1. `>RL51 A:prog.obj TO A:prog.abs`

In this example, the input list has one file (prog.obj in directory A:); RL51 links all the modules in this file into the output file (prog.abs). (For clarity, this and other examples omit the directory in which RL51 resides; the examples assume RL51 resides in the root directory.)

2. `>RL51 a:samp1.obj, a:samp2.obj, a:samp3.obj &`  
`>> TO b:samp.abs`

In this example, the input list has three files. RL51 links all the modules in each of these files into the output file. (Note that the `>>` in the second line of the example is generated by the system in response to the continuation character `&` on the first line of the example.)

3. `>RL51 A:PROG1.OBJ (MOD1, MOD3), A: PROG2.OBJ &`  
`>> (MOD2) TO A:PROG3.ABS`

Here, the input list has two input files (PROG1.OBJ and PROG2.OBJ). From PROG1.OBJ, only the modules named MOD1 and MOD3 are to be linked into the output file; any other modules in file PROG1.OBJ are ignored by RL51. From PROG2.OBJ, only the module named MOD2 is to be linked.

4. `>RL51 a:plmprg.obj, a:util51.lib, a:ios1.lib, &`  
`>> plm51.lib`

The example introduces a typical linking using libraries. Here, plmprg.obj is linked with two private libraries and with the mandatory library plm51.lib (which must be used if modules generated by plm51 participate in the linkage).

5. `>RL51 a:exempl.obj, cotrig.lib, trig.lib, &`  
`>> cotrig.lib`

Interaction between libraries (i.e., libraries that reference each other) may sometimes require the same library to be mentioned twice in the input list.

In the preceding example, cotrig.lib contains the COTANGENT and COSINE trigonometric functions, trig.lib contains the SIN and TANGENT functions, and exempl.obj references the COTANGENT function.

Because COTANGENT equals 1/TANGENT, trig.lib must be specified to resolve the reference to the TANGENT function. Also, because TANGENT equals SINE/COSINE, cotrig.lib must be respecified to resolve the reference to the COSINE function.

## Output File

The output filename is the name of the disk file that is to receive the absolute object module.

If the output file name is omitted, RL51 creates a filename for the output file by removing the extension from the first filename in the input list and using the drive and root name only. If this input file contains no extension, a fatal error occurs. For example, the command:

```
RL51 PROG1
```

is illegal since the output filename defaults to PROG1.

If there is already a file on the target drive with the name of the output file, that file is overwritten by the new output file.

## Examples

Following are examples of RL51 output file—

1. `>RL51 a:prog.obj TO c:prog`

This example specifies file prog in directory c: as the output file.

2. `>RL51 C:PROG.OBJ`

This example uses the default output file generated by RL51. The effect is the same as the first example; the output file becomes c:prog.

3. `>rl51 a:sample1.obj, a:sample2.obj TO &  
>> c:\myfile\sampl.abs`

In this example, the output file is in a different directory than the input files, and the directory, filename SAMPL, and the extension .ABS are specified.

## Controls

After the output filename, you can add a list of controls to select options for listing, linking, and locating the output. Use blanks (not commas) to separate controls in the list. The same control may not appear more than once in the list; if a duplicate control is encountered, a fatal error results and the program aborts. The next several sections explain the controls and give examples.

### Listing Controls

The listing file output by RL51 can contain a link summary, a symbol table, an IXREF report, and a list of error messages. The link summary can contain a memory map of the linked segments.

The listing controls are the PRINT option, the PAGEWIDTH control, the MAP option, the SYMBOLS option, the PUBLICS option, the LINES option, and the IXREF option. These controls allow you to specify the file or device to receive the output listing, to omit the listing file altogether, to omit the map from the link summary, or to omit local symbols, public symbols, or line numbers from the symbol table. You may also specify if you wish to have the IXREF report generated, and the specific page width to be used.

#### NOTE

The information in the listing file is taken from the input object modules. If these are generated without the DEBUG option, the SYMBOLS, PUBLICS, and LINES information will not be available for listing.

### PRINT/NOPRINT

The print options control the destination of the list file.

To direct the list file to a disk file, the print control format is

```
PRINT ([directory/device] filename[.ext] )
```

#### Example

```
>RL51 a:sample1.obj &  
>> print (a:sample.lst)
```

To direct the list file to a device other than a disk file, the print control format is

```
PRINT (:device:)
```

where

*device*

is a device code. Common devices are CO (console), LP (line printer), TO (terminal other than console), and VO (video terminal screen).

If you omit the print control, or if you enter the command word PRINT without a filename or device name, RL51 creates a disk file for the listing. The name of the default listing file has the same root as the output filename and has an extension of M51; the drive number is also the one used in the output filename.

### Example

```
>RL51 A:PROG.OBJ, A:PROG1.OBJ TO B:PROG2.ABS
```

The output listing filename may not be the same as the output filename or any of the filenames in the input list. If the listing file duplicates an input or output filename, a fatal error results. If the listing filename already exists on the target directory, the old file with that name is overwritten by the new listing file.

The NOPRINT option specifies that no output listing file is to be produced. NOPRINT overrides the MAP, SYMBOLS, PUBLICS, LINES and IXREF controls.

### PAGEWIDTH

The PAGEWIDTH control specifies the maximum number of columns per line in the print output file. The control takes the form

```
PAGEWIDTH (width)
```

where

*width*

is an unsigned number which specifies the maximum page width to be used.

The allowable range for *width* is 72 to 132. The default PAGEWIDTH is 78.

### Listing Switches

The MAP, SYMBOLS, PUBLICS, LINES and IXREF controls select what portions of the listing files are to be generated. The default of any switch (with the exception of IXREF) is the positive form (MAP, SYMBOLS, PUBLICS, and LINES). Table 3-2 summarizes the listing switches.

### IXREF/NOIXREF

This control specifies whether or not to produce the inter-module cross reference report. If IXREF is specified, the report is appended to the print file.

A selection list may be added to the positive form (only) of the IXREF control. A selection list causes RL51 to output or suppress output of various selected entries to



Table 3-2. Listing Switches

Switch	Effect
MAP	Output memory map to link summary
NOMAP	Suppress memory map
SYMBOLS	Output local symbols to symbol table
NOSYMBOLS	Suppress local symbols
PUBLICS	Output public symbols to symbol table
NOPUBLICS	Suppress public symbols
LINES	Output line numbers to symbol table (high-level language translators only)
NOLINES	Suppress line numbers
IXREF	Append intermodule cross-reference report to print file
NOIXREF	Suppress the intermodule cross-reference report

the IXREF report. An entry consists of a symbol and a module where this symbol is referenced (either as public or as external). The general form of the IXREF control is

```
IXREF [(selection-item [ , . . . ] )]
```

where

*selection-item* is either (NO)GENERATED or (NO)LIBRARIES. If IXREF is specified and any of the selection items are omitted, the missing selection item assumes its positive form. A selection item may appear at most once.

The selection-items are best explained by describing the effect of their negative form.

The NOGENERATED control causes RL51 to suppress output of entries whose symbol name begins with a question mark (?); such symbols are usually PL/M-51 generated symbols. The GENERATED form of the control causes RL51 to output such entries also.

The NOLIBRARIES control causes RL51 to suppress output of entries whose module resides within a library. The LIBRARIES form of the control causes RL51 to include all libraries in the IXREF report.

The selection list is used to control the number of entries collected for the IXREF report. This is needed when an excessive number of IXREF entries make it impossible for RL51 to generate the IXREF report.

### Examples

1. `>RL51 a:prog.obj nosymbols nopublics noline`

Because the default for any listing switch (except ixref) is the positive form, the main use of the switches is to suppress unwanted information. The invocation given in this example will suppress the entire symbol table.

2. `>rl51 a:prog.obj print (a:prog.m51) nomap nosb &  
>> noli`

In this example, only the public symbols will be printed (no map or other symbols or lines). Note the use of abbreviations (nosb for nosymbols and noli for noline) to save keystrokes. A complete list of abbreviated forms appears at the end of

Chapter 3. Note that the blank separating print from its parameters is optional; you could also use `print(a:prog.m51)`.

3. 

```
>RL51 a:prog.obj, a:procs.obj, a:plm51.lib &
>> ixref(nogn)
```

This example suppresses generated symbols from the ixref report. Using the `nogn` (nogenerated) selection item prevents PL/M-51 run-time library procedures from being written to the ixref report.

## Linking Controls

The linking controls allow you to name the resultant output module and to specify which debug information is to be copied to the output module.

### NOTE

In order to obtain the debug information (SYMBOLS, PUBLICS, or LINES), the `DEBUG` control must be included in the invocation line for the translator used to produce the input modules.

## NAME

The `NAME` control allows you to name the output module. The format is

`NAME (module-name)`

If the `NAME` control is not used, the output module-name defaults to the name of the first input module processed.

### Example

```
>RL51 a:samp11.obj, a:samp12.obj TO a:sample.abs &
>> name(SAMPLE_PROGRAM)
```

In this example, the name `SAMPLE_PROGRAM` is assigned to the output module. Note that the blank between `NAME` and its parameter is optional and can be omitted.

## Linking Switches

The `DEBUGSYMBOLS`, `DEBUGPUBLICS`, and `DEBUGLINES` controls select what kinds of debug information are to be included in the output file. The default of any switch is always the positive form (`DEBUGSYMBOLS`, `DEBUGPUBLICS`, and `DEBUGLINES`). Table 3-3 summarizes the linking switches.

### Examples

1. 

```
>RL51 a:prog1.obj nodebugsymbols nodebuglines
```

Because the linking switches default to the positive form, you will usually use the negative forms to suppress unwanted debug information in the output file. In this example, the output file contains only the information for the public symbols.

2. 

```
>RL51 a:prog1.obj nodp nodl
```

In this example, only the local symbols are output to the absolute file. Note the use of abbreviations (`nodp` for `nodebugpublics` and `nodl` for `nodebuglines`).

Table 3-3. Linking Switches

Switch	Effect
DEBUGSYMBOLS	Copies local symbol information to output file
NODEBUGSYMBOLS	Suppresses local symbols
DEBUGPUBLICS	Copies public symbol information to output file
NODEBUGPUBLICS	Suppresses public symbols
DEBUGLINES	Copies line number information (high-level language translators only) to output file
NODEBUGLINES	Suppresses line numbers

## Locating Controls

The locating controls allow you to assign absolute addresses to relocatable segments, to specify the ordering of relocatable segments of a given type in memory, and to force allocation of segments into a specific range of addresses.

## Allocation Sequence

The system allocates memory in accordance with segment attributes and locating controls, using a fixed order of precedence. The precedence of the allocating operations (grouped by type of memory space) is as follows:

### Internal Data Space:

- Absolute BIT, DATA, and IDATA segments, and register banks
- Segments specified in a PRECEDE control in the RL51 command
- Segments specified in a BIT control in the RL51 command
- DATA type segments with relocation equal to BIT-ADDRESSABLE
- Other relocatable bit segments
- Segments specified in a DATA control in the RL51 command
- DATA type segments with relocation equal to UNIT-aligned
- Segments specified in an IDATA control in the RL51 command
- Other relocatable IDATA segments, except ?STACK
- Segments specified in a STACK control in the RL51 command
- ?STACK, if it is IDATA and has not been specified in any other locate control

### External Data Space:

- Absolute external data segments
- Segments specified in an XDATA control in the RL51 command
- Other relocatable external data segments

### Code Space:

- Absolute code segments
- Segments specified in a CODE control in the RL51 command
- Other relocatable code segments

### NOTE

In most cases, the allocation algorithm will produce a workable solution without requiring the user to enter any locating controls in the RL51 command. These controls are intended for the experienced user, in cases where running RL51 without them does not give a good enough result.

## Format Summary

The locating controls have the format

*control* ( *segment* [ , . . . ] )

where

*segment* : \* *segment-name* [ ( *base-address* ) ]

The segments specified in the locating controls are allocated in the order they appear; the first segment is assigned the lowest possible address, and succeeding segments receive higher and higher addresses.

The user has the option of specifying the base address of any or all segments. Segments with specified base addresses must appear in the list in ascending numerical order. Segments named in a locating control with a specific base address are allocated at that address irrespective of segment overlap or segment type contradiction, as long as ascending order is maintained. Base addresses are byte addresses except for the BIT locating control, where addresses are bit addresses in the bit space 0 to 127).

## Table of Locating Controls

Table 3-4 lists the locating controls in order of precedence. The first column gives the name of the control. The second column describes the address space affected by the control. The third column gives the address range for segments within each control. The last column shows what types of segments are allowed for each control; for each valid type, the column also shows the allowable relocation attributes. (Refer to the *MCS-51 Macro Assembler User's Guide* and *PL/M-51 User's Guide* for details on segment types and relocation attributes.)

## Notes On Locating Controls

The following notes refer to table 3-4.

1. Bit addresses for non-BIT segments in the BIT control must be on byte boundaries; that is, they must be divisible by eight. (BIT-type segments can be aligned on bit boundaries.)

Table 3-4. Locating Controls

Control	Address Space	Address Range (Hex)	Segment Types (and Attributes)
PRECEDE	Register banks and bit-addressable space in on-chip data RAM	00H-2FH	DATA (UNIT-aligned); IDATA
BIT	Bit-addressable space in on-chip data RAM	00H - 7FH (see note 1)	BIT; DATA; IDATA
DATA	Directly-addressable on-chip data RAM	00H - 7FH	DATA (UNIT-aligned); IDATA
IDATA	Indirectly-addressable on-chip data RAM	00H - 0FFH (see note 2)	IDATA
STACK	Same as IDATA (see note 3)	Same as IDATA	Same as IDATA
XDATA	External data RAM	0 - 0FFFFH	XDATA
CODE	Code memory	0 - 0FFFFH	CODE

- The range of addresses for the IDATA control is dependent on the target machine. See the RAMSIZE control later in this chapter.
- The STACK control specifies which segments are to be allocated uppermost in the IDATA space. The memory accessed starts after the highest on-chip RAM address occupied by any previously allocated segment and continues to the top of the IDATA space.

**NOTE**

This control has no other effect on any segments.

The IDATA ?STACK segment, if it exists, is placed higher than segments that were mentioned in the STACK control.

The STACK control provides a convenient way to handle the stack (usually for ASM51-based application, where ?STACK is not used).

First, assign the stack pointer (SP) to a relocatable segment; consider the following ASM51 example:

```
STACK_AREA SEGMENT IDATA      ; SEGMENT directive in source.
    DS          10H           ; Reserve 16 bytes for stack.

    . . . . .                ; Other CODE instructions.

    MOV         SP, #STACK_AREA-1 ; Initialize SP.
```

Then, at relocation time, specify the segment named STACK\_AREA in a STACK locating control:

```
RLS1 ... STACK (STACK_AREA)
```

where

ellipsis (...) represents the rest of the invocation line exclusive of the STACK control.

**NOTE**

If the application contains modules produced by PL/M-51, the ?STACK should be used as the stack segment.

**Examples**

- ```
>RLS1 A:PROG1.OBJ, A:PROG2.OBJ TO A:PROG.ABS &
>> PRECEDE (MESSAGE1) XDATA (ARRAY1 (256), &
>> ARRAY2 (512))
```

In this example, the DATA (or IDATA) segment names MESSAGE1 will be allocated space in on-chip RAM in the lowest available location, overlapping the BIT space if necessary. The XDATA control specifies that the two arrays are to be located at specific addresses (e.g., for debugging).

- ```
>RLS1 A:TEST.OBJ STACK (STACK_AREA)
```

Here, the STACK control allocates the uppermost portion of IDATA space for the segment named STACK\_AREA.

- ```
>RLS1 APROG.OBJ, BPROG.OBJ, PLM51.LIB &
>> CODE (MOD1 (4000H), MOD2, MOD3)
```

Here, the CODE control allocates space in code memory for segments MOD1, MOD2, and MOD3. MOD1 is aligned at location 4000H. MOD2 and MOD3 are assigned contiguous addresses after MOD1.

## Configuration Controls

The configuration controls are used to describe the actual configurations that objects are aimed to.

This group contains the RAMSIZE control.

### RAMSIZE

The RAMSIZE control format

`R A M S I Z E ( value )`

where

*value* is a number in the range 128 to 255.

RAMSIZE specifies the maximum amount of on-chip RAM that may be allocated for the user program. The default value for RAMSIZE is 128 (as is the case for the 8051). If the object is aimed at more than one configuration of the MCS-51 family, specify the MINIMUM of all on-chip RAM sizes among all machines you want to link.

The sole use of this control is to enable RL51 to check on-chip memory size constraints at RL-time and thus avoid confusion at ICE-time.

## OVERLAY/NOOVERLAY Controls

The linker allows overlaying of on-chip RAM segments among modules, under the specification of the OVERLAY control. Two segments can be overlaid if all the following conditions exist:

- The segments have the same type (DATA, IDATA, BIT, or BITADDRESSABLE).
- The segments use the same register bank (determined by the USING attribute or the REGISTERBANK control).
- The segments are marked as overlayable. Currently, this is done only by the PL/M-51 compiler. ASM51 (V2.1 and lower) lacks this feature. Therefore, assembler segments are considered non-overlayable.
- The segments belong to disjoint modules. That is, no procedure in one module can directly or indirectly call a procedure from the other.

The default is NOOVERLAY. No overlaying of on-chip RAM segments is done by the linker.

The general form of the OVERLAY control is as follows:

`O V E R L A Y [ ( overlay-unit [ , . . . ] ) ]`

where

*overlay-unit* is *ov-module-name* calls *ov-module-name*.

*ov-module-name* is a legal RL51 module name or \*, which stands for all the module names.

*calls* is > or !.

## OVERLAY

If the OVERLAY control appears in the invocation line without arguments, the linker assumes that no intra-module calls exist except for those deducible from the PUBLIC-EXTERNAL declarations, and that overlaying of all overlayable segments is safe.

## NOOVERLAY

The linker does not overlay data segments.

## OVERLAY (A > B) or (A ] B)

If the OVERLAY control appears in the invocation line with arguments, it indicates that there are invisible calls between modules. In the OVERLAY control syntax, either the greater than sign (>), or the right square bracket (]) may be used in the calls relationship. The greater than sign will be used in the text. The notation A > B means that module A calls module B. In this case, the linker overlays all overlayable segments, except that segments from A are not overlaid by segments from B. Note that the added connection can prevent other segments from overlaying. For example, if the segment A was overlaid with the segment D, and B calls D (visibly by PUBLIC-EXTERNAL declarations), then the effect of A > B is that A and D will not be overlaid, since A can call D through B.

## OVERLAY (A > \*, \* > B) or (A ] \*, \* ] B)

A module can be declared as non-overlayable in two ways. The argument A > \* indicates that the module A calls all other modules. On the other hand, \* > A means every module calls A. In either case, no segments from A will be overlaid. The effect of each form depends on the nature of A. For example, if the \* > A form is used and A visibly calls all other modules, then every module can call (through A) each other module. In this case, the linker will not perform any overlays.

The overlaying of data segments in on-chip RAM has the following restrictions:

- The OVERLAY control cannot be invoked with the IXREF selection items NOGENERATED or NOLIBRARIES. RL51 generates an error if either one is specified.
- Combined segments and segments appearing in locating controls are not overlaid by the linker.

Following is an example in which two disjoint modules share the same on-chip RAM area:

```
mod1: D0;

    THREE_BEARS: PROCEDURE PUBLIC;
        DECLARE LITTLE_BEARS_BED BYTE;
        IF BOOLEAN (LITTLE_BEARS_BED) THEN
            CALL MSG(,('SOMEONE'S BEEN IN MY BED!'),0);
        LITTLE_BEARS_BED = 0;
    END THREE_BEARS;

END mod1;  -
```

```

mod2: DO;

    GOLDILOCKS: PROCEDURE PUBLIC;
        DECLARE SPARE_BED BYTE;
        SPARE_BED = 1;
    END GOLDILOCKS;

END mod2;

main_story: DO;

    THREE_BEARS: PROCEDURE EXTERNAL; END;
    GOLDILOCKS: PROCEDURE EXTERNAL; END;

    CALL THREE_BEARS;
    CALL GOLDILOCKS;
    CALL THREE_BEARS;

END main_story;

```

In this example, the linker reserves the right to use the `LITTLE_BEARS_BED` as a `SPARE_BED` because the two procedures are never active simultaneously.

To perform overlaying, the linker must determine which procedures are active simultaneously. To do this, the linker assumes that all `CALL`s can be executed. For example, if procedure A calls procedure B, and B calls procedures C and D, then the linker can overlay RAM variables from C only with the RAM variables of D.

The linker, however, looks only at the `PUBLIC-EXTERNAL` declarations. It assumes that any reference to an `EXTERNAL` procedure will be executed, but ignores the possibility of hidden calls. The arguments to the `OVERLAY` control are therefore needed to specify those interconnections between modules that cannot otherwise be detected by the linker.

Such situations arise if the interconnection is done by a computed call to an external procedure whose address is not determined by a simple `PUBLIC-EXTERNAL` relationship. For example, module A imports from module B a public variable that contains the address of a local or public procedure in B. Module A then performs a computed call to the procedure in B. The rule can be stated as follows: The linker assumes a connection from module A to module B if there exists an external reference in A to a public procedure in B. In all other cases, hidden connections must be explicitly given as arguments to the `OVERLAY` control.

Following is an example of a computed call to an external procedure:

```

MOD1: DO;

    DECLARE I_O_CLEAR WORD EXTERNAL;
    .
    .
    CALL I_O_CLEAR;
    .
    .
END MOD1;

```



In another module, you have:

```
MOD2: DO;

    DECLARE I_O_CLEAR WORD PUBLIC;

    READER: PROCEDURE;

        I_O_ERROR: PROCEDURE;
        .
        END I_O_ERROR;

        I_O_SUCCESS: PROCEDURE;
        .
        END I_O_SUCCESS;

        IF ERR_CODE <> 0
            THEN I_O_CLEAR = .I_O_ERROR;
            ELSE I_O_CLEAR = .I_O_SUCCESS;
        . . .

    END READER;

END MOD2;
```

In the above procedure, MOD1 invokes a procedure defined in MOD2. To prevent the linker from overlaying on-chip RAM variables of MOD2 with on-chip RAM variables of MOD1, the following form of the OVERLAY control must be used:

```
OVERLAY (MOD1 > MOD2)
```

Overlaying can be a good way of economizing on-chip RAM space; however, overlaying may, in some cases, give worse results. For example, if most procedures call one another, the resulting segments will expand, making it more difficult for the linker to allocate a few large segments than many small ones.

The outcome of the overlaying process can be checked by inspecting the link map. All overlaid segments are indicated by **\*\*OVERLAP\*\***. Warning (4), DATA SPACE MEMORY OVERLAP, is not generated for those segments.

## Abbreviations for Command Words

Most of the command words in the RL51 command have short forms to save you keystrokes over the full spellings. Here is a list of the command words and their abbreviations.

| Command Word | Abbreviation |
|--------------|--------------|
| BIT          | BI           |
| CODE         | CO           |
| DATA         | DT           |
| DEBUGLINES   | DL           |
| DEBUGPUBLICS | DP           |
| DEBUGSYMBOLS | DS           |
| GENERATED    | GN           |
| IDATA        | ID           |
| IXREF        | IX           |
| LIBRARIES    | LB           |

|                |      |
|----------------|------|
| LINES          | LI   |
| MAP            | MA   |
| NAME           | NA   |
| NODEBUGLINES   | NODL |
| NODEBUGPUBLICS | NODP |
| NODEBUGSYMBOLS | NODS |
| NOGENERATED    | NOGN |
| NOIXREF        | NOIX |
| NOLIBRARIES    | NOLB |
| NOLINES        | NOLI |
| NOMAP          | NOMA |
| NOOVERLAY      | NOOL |
| NOPRINT        | NOPR |
| NOPUBLICS      | NOPL |
| NOSYMBOLS      | NOSB |
| OVERLAY        | OL   |
| PAGEWIDTH      | PW   |
| PRECEDE        | PC   |
| PRINT          | PR   |
| PUBLICS        | PL   |
| RAMSIZE        | RS   |

The RL51 program produces three outputs: console displays, a listing file, and the absolute object module file. This chapter describes these outputs and gives examples. As discussed in Chapter 3, the listing controls in the RL51 command allow the user to suppress some information in the listing file, and the linking controls can suppress some information in the absolute object file.

## Console Display

The console displays produced by RL51 consist of a sign-on message and any error messages that occur. The sign-on is as follows:

```
system-id MCS-51 RELOCATOR AND LINKER Vx.y
```

where

*x.y* is the version number.

## Listing File

RL51 produces a listing file unless it is suppressed in the RL51 invocation. The RL51 listing file contains:

- A summary of the link and locate process
- A symbol table, as specified in the RL51 invocation
- An inter-module cross-reference listing (IXREF)
- Error messages detected by RL51

## Link Summary

A sample of a link summary is shown in figure 4-1. The summary includes the following kinds of information:

- A header echoing the RL51 invocation.
- Input modules included in the link process. Input modules are identified by module name and file name.
- A link map (unless suppressed by the NOMAP control). The map lists all allocated segments, giving the type, base address, and length of each segment. The map also identifies segment overlaps and gaps in the memory space.
- A list of segments that were ignored in the link process. If any segments were ignored, the reasons for doing so will be reported later as an error.
- A list of unresolved external symbols. An external symbol is unresolved when it is not matched by a public symbol in one of the input modules. Each occurrence of an unresolved external symbol in a module will be reported later as an error.
- A list of all symbols that were ignored in the locate process. A symbol is ignored when the same name appears as a public symbol in different modules, or has attributes that are incompatible with external references, or belongs to an ignored segment. Each occurrence of an ignored symbol in a module will be reported later as an error.

system-id MCS-51 RELOCATOR AND LINKER, Vx.y INVOKED BY:  
 RL51 FILE1.EXT(MOD1,MOD2), FILE2.EXT TO OUTFIL.EXT &  
 NAME (EXAMPLE) MAP PRINT (:LP:)

# INPUT MODULES INCLUDED

FILE1.EXT(MOD1)  
 FILE1.EXT(MOD2)  
 FILE2.EXT(MOD3)

# LINK MAP FOR OUTFIL.EXT(EXAMPLE)

|             | TYPE  | BASE    | LENGTH  | RELOCATION | SEGMENT NAME |
|-------------|-------|---------|---------|------------|--------------|
|             | REG   | 0000H   | 0008H   |            | "REG BANK 0" |
|             | DATA  | 0008H   | 0010H   | UNIT       | DATA_SEG_1   |
|             | DATA  | 0014H   | 0008H   | ABSOLUTE   |              |
| **OVERLAP** | REG   | 0018H   | 0008H   |            | "REG BANK 3" |
|             | BIT   | 0020H   | 0001H.6 | UNIT       | A_BIT_SEG    |
|             |       | 0021H.6 | 0000H.2 |            | ***GAP***    |
|             | DATA  | 0022H   | 0001H   | BITADDR    | DATA_SEG_2   |
|             | DATA  | 0023H   | 0008H   | ABSOLUTE   |              |
|             | IDATA | 002EH   | 0042H   | UNIT       | STACK_SEG    |
|             |       | 0070H   | 0010H   |            | ***GAP***    |
|             | XDATA | 0000H   | C000H   | UNIT       | DYNAMIC_MEM  |
|             | CODE  | 0000H   | 1389H   | UNIT       | PROC1        |
|             |       | 1389H   | 0477H   |            | ***GAP***    |
|             | CODE  | 1800H   | 07A5H   | INBLOCK    | PROC2        |

IGNORED SEGMENTS  
 DYNAMIC POOL

UNRESOLVED EXTERNAL SYMBOLS  
 INVERT

IGNORED SYMBOLS  
 BIT256

Figure 4-1. Link Summary

## NOTE

- For bit addresses, the display format is *byte-address.bit-address* (example: 0020H.7 for bit 7 of byte 0020H). However, when bit 0 of a byte is referenced, only the byte address is displayed (the .0 is not displayed).
- References to an unresolved external symbol, an external symbol referring to an ignored public symbol, or a reference to an ignored segment will produce additional error messages.

## Symbol Table

The listing file contains a symbol table as specified by the SYMBOLS, PUBLICS, and LINES controls in the RL51 invocation. A sample symbol table is shown in figure 4-2.

## SYMBOL TABLE FOR OUTFILE.EXT(EXAMPLE)

| VALUE     | TYPE    | NAME           |
|-----------|---------|----------------|
| -----     | ----    | ----           |
| -----     | MODULE  | MEMORY         |
| D:0032H   | PUBLIC  | LOW_MEM_PTR    |
| B:0020H   | PUBLIC  | INIT_FLAG      |
| B:0020H.1 | PUBLIC  | FULL_FLAG      |
| D:0034H   | PUBLIC  | HIGH_MEM_PTR   |
| X:0000H   | PUBLIC  | DYNAMIC_MEMORY |
| -----     | PROC    | ALLOCATE       |
| D:0064H   | SYMBOL  | NUM_BYTES      |
| D:0066H   | SYMBOL  | POOL_SELECTOR  |
| D:0068H   | SYMBOL  | ALLOC_PTR      |
| B:0020H.2 | SYMBOL  | FLAG           |
| C:0000H   | LINE#   | 19             |
| C:007H    | LINE#   | 20             |
| C:0010H   | LINE#   | 21             |
| C:0013H   | LINE#   | 22             |
| -----     | DO      |                |
| D:006AH   | SYMBOL  | I              |
| C:0018H   | LINE#   | 23             |
| C:0021H   | LINE#   | 24             |
| C:0028H   | LINE#   | 25             |
| C:002FH   | LINE#   | 26             |
| C:0032H   | LINE#   | 27             |
| -----     | ENDDO   |                |
| C:0037H   | LINE#   | 28             |
| C:0040H   | LINE#   | 29             |
| C:004FH   | LINE#   | 30             |
| C:0057H   | LINE#   | 31             |
| C:005FH   | LINE#   | 32             |
| C:0068H   | LINE#   | 33             |
| C:006FH   | LINE#   | 34             |
| C:0076H   | LINE#   | 35             |
| C:0082H   | LINE#   | 36             |
| C:008FH   | LINE#   | 37             |
| C:0094H   | LINE#   | 38             |
| -----     | ENDPROC | ALLOCATE       |
| -----     | ENDMOD  | MEMORY         |

Figure 4-2. Symbol Table

## NOTE

The information in the listing file is taken from the input object modules. If these are generated without the DEBUG option, the SYMBOLS, PUBLICS, and LINES information will not be available for listing.

The symbol table contains scope definitions and information about the symbols and line numbers. Scope definition identifies the module, DO block or procedure that contains the symbol or line number. Note that when the table contains only public symbols (i.e., NOSYMBOLS and NOLINES controls are in effect), scope definition is by module only.

Each entry in the table consists of three parts, as follows:

- **VALUE.** The value is the absolute address of the symbol. The address is prefixed with a letter indicating the type of address space (C, code; D, internal data; I, indirect internal data; B, bit space; X, external data; N, typeless number). A byte address (or a bit address on a byte boundary) is shown as a four-digit hexadecimal number (example: 00E0H). A bit address (unless it is on a byte boundary) is shown as a byte address followed by a period and the bit offset (1 through 7) into the byte.
- **TYPE.** The type field identifies the entry as a local symbol (SYMBOL), a public symbol (PUBLIC), segment (SEGMENT), or a line number (LINE#).
- **NAME.** The name field gives the name of the symbol, or the number of the line.

For scope definition, a line is printed for the beginning and end of each block. The TYPE field shows the type of block (MODULE, DO, or PROC for PROCEDURE), and the end of each block (ENDMOD, ENDDO, ENDPROC). The NAME field shows the name of the block, if any.

#### NOTE

Line number information and scope definitions other than MODULE are applicable only to object files produced by high-level language translators (e.g., PL/M-51).

### Inter-Module Cross-Reference Report (IXREF)

The listing file contains an IXREF report as specified by the IXREF control and its associated selection list in the RL51 invocation. A sample IXREF report is shown in figure 4-3.

The IXREF report consists of an alphabetically sorted list of symbols. Each such symbol begins a new line and represents a symbol that was declared as PUBLIC or EXTERNAL in at least one of the input modules. Each symbol is followed by its corresponding address space, followed by a semicolon. To the right of the semicolon starts a list of modules in which the symbol was declared PUBLIC or EXTERNAL. The first module name in the list is the one in which the symbol was declared PUBLIC. If a symbol is unresolved, or if a symbol is defined in a library and the NOLIBRARY selection item is in effect, then the string \*\* UNRESOLVED \*\* appears in front of the modules list.

### Error Messages

RL51 displays error messages on the console and copies them to the end of the listing file unless the listing file is suppressed.

RL51 error messages describe warnings, errors, and fatal errors. A warning is a detected condition that may or may not be what the user desired; a warning does not terminate the link/locate operation. An error does not terminate operation, but probably results in an output module that cannot be used. A fatal error terminates operation of RL51.

Refer to Appendix B for a list of the error messages and probable causes.

## INTER-MODULE CROSS-REFERENCE LISTING

| NAME               | USAGE  | MODULE NAMES                       |
|--------------------|--------|------------------------------------|
| ?CHECK_EQ?BYTE     | DATA;  | CHKEQ TESBAS                       |
| ?CHECK_EQ_BITS?BIT | BIT;   | CHKEQ                              |
| ?P0008             | CODE;  | ?P0008 TESBAS                      |
| ?P0015             | CODE;  | ?P0015 TESBAS                      |
| ?P0016             | CODE;  | ?P0016 TESBAS                      |
| ?PIHOR             | CODE;  | TESBAS ?PIVOR                      |
| ?PIVOR             | CODE;  | ?PIVOR TESBAS                      |
| ?PSWOR             | NUMB;  | TESBAS ?PIVOR                      |
| CHECK_EQ           | CODE;  | CHKEQ TESBAS                       |
| CHECK_EQ_BITS      | CODE;  | CHKEQ                              |
| CHECK_EXIT         | CODE;  | CHKEQ                              |
| CHECK_INIT         | CODE;  | CHKEQ                              |
| PUB00              | CODE;  | MODULE_0 MODULE_1 MODULE_2         |
| PUB01              | CODE;  | MODULE_0 MODULE_1 MODULE_2         |
| PUB02              | CODE;  | MODULE_0 MODULE_1 MODULE_2         |
| PUB03              | CODE;  | ** UNRESOLVED ** MODULE_1 MODULE_2 |
| PUB04              | CODE;  | MODULE_0 MODULE_1 MODULE_2         |
| PUB05              | CODE;  | MODULE_0 MODULE_1 MODULE_2         |
| PUB06              | CODE;  | ** UNRESOLVED ** MODULE_1 MODULE_2 |
| PUB07              | CODE;  | MODULE_0 MODULE_1 MODULE_2         |
| PUB08              | CODE;  | MODULE_0 MODULE_1 MODULE_2         |
| PUB09              | CODE;  | MODULE_0 MODULE_1 MODULE_2         |
| PUB10              | CODE;  | MODULE_0                           |
| PUB11              | XDATA; | MODULE_0                           |
| PUB12              | DATA;  | MODULE_0                           |
| PUB13              | IDATA; | MODULE_0                           |
| PUB14              | BIT;   | MODULE_0                           |
| PUB15              | NUMB;  | MODULE_0                           |
| PUB16              | CODE;  | MODULE_0                           |
| PUB17              | CODE;  | MODULE_0                           |
| PUB18              | CODE;  | MODULE_0                           |
| PUB19              | CODE;  | MODULE_0                           |
| PUBX0              | CODE;  | MODULE_1 MODULE_0                  |
| PUBX1              | CODE;  | MODULE_1 MODULE_0                  |
| PUBY0              | CODE;  | ** UNRESOLVED ** MODULE_1 MODULE_2 |
| PUBZ0              | CODE;  | ** UNRESOLVED ** MODULE_1          |

Figure 4-3. IXREF Listing

## Absolute Object File

The linking and locating process combines one or more relocatable object files into one absolute object file. The absolute object file contains one module; the absolute module consists of

- A module header record that identifies the module.
- A set of intermixed content and debug records. The content records contain the program code. The debug records contain the location and scope of local symbols, public symbols, segment symbols, and line numbers, as specified by the DEBUG-SYMBOLS, DEBUGPUBLICS, and DEBUGLINES controls in the RL51 invocation.
- A module end record that verifies the module name.

## Examples of Program Development

---

This chapter shows three brief examples of program development using ASM51, PL/M-51, and RL51. The first example is the sample program discussed in the *ASM51 User's Guide*; the example shows how to assemble each of the three modules, then link and locate them into a single absolute object module with RL51. The second example is a short program that illustrates the use of the locating controls. The third example shows the use of RL51 with PL/M-51 modules, emphasizing the library process.

### Using Multiple Modules

The first example is a program of three modules, named SAMPLE, CONSOLE\_IO, and NUM\_CONVERSION. The source for these modules is in three files, SAMP1.A51, SAMP2.A51, and SAMP3.A51, respectively. To assemble these modules, invoke the assembler as follows:

```
ASM51 SAMP1.A51 DEBUG
```

```
ASM51 SAMP2.A51 DEBUG
```

```
ASM51 SAMP3.A51 DEBUG
```

Note that this example assumes the three source files are on the same directory or device as the assembler and linker/locator, and that the output file will be sent to the same directory or device. The assembler invocations use the DEBUG control to have the symbol tables output to the object files for the three modules.

After assembly is complete, the system has created object files SAMP1.OBJ, SAMP2.OBJ, and SAMP3.OBJ, and listing files SAMP1.LST, SAMP2.LST and SAMP3.LST. The three listing files are shown in figures 5-1, 5-2, and 5-3.

To link and locate the three modules, enter the command

```
RL51 SAMP1.OBJ, SAMP2.OBJ, SAMP3.OBJ &  
**TO SAMPLE &  
**PRINT (SAMPLE.LST) SYMBOLS LINES PUBLICS
```

After the RL51 program has executed, the system has placed the absolute object module in file SAMPLE, and an output file with information on the link and locate process in file SAMPLE.LST. The output file also contains symbol table information as requested by the SYMBOLS, LINES, and PUBLICS controls. The listing file is shown in figures 5-1 through 5-3; figure 5-4 shows the output file.



```

MCS-51 MACRO ASSEMBLER SAMPLE
system-id MCS-51 MACRO ASSEMBLER Vx.y
OBJECT MODULE PLACED IN SAMP1.OBJ
ASSEMBLER INVOKED BY: ASMS1 SAMP1.A51 DEBUG
LOC OBJ
LINE SOURCE
1 NAME SAMPLE
2 ;
3 EXTRN code (put_crlf, put_string, put_data_str)
4 EXTRN code (get_num, binasc, ascbin)
5 ;
6 CSEG
7 ; This is the initializing section. Execution
8 ; always starts at address 0 on power-up.
9 ORG 0
10 MOV TMOD,#00100000B ; Set timer to auto-reload
11 MOV TH1,#(-253) ; Set timer for 110 BAUD
12 MOV SCON,#1011010B ; Prepare the Serial Port
13 SETB TR1 ; Start clock
14 ;
15 ; This is the main program. It's an infinite loop,
16 ; where each iteration prompts the console for 2
17 ; input numbers and types out their sum.
18 START:
19 ; Type message explaining how to correct a typo
20 MOV DPTR,#typo_msg
21 CALL put_string
22 CALL put_crlf
23 ; Get first number from console
24 MOV DPTR,#num1_msg
25 CALL put_string
26 CALL put_crlf
27 MOV R0,#num1
28 CALL get_num
29 CALL put_crlf
30 ; Get second number from console
31 MOV DPTR,#num2_msg
32 CALL put_string
33 CALL put_crlf
34 MOV R0,#num2
35 CALL get_num

```

Figure 5-1. SAMP1 Listing File

```

0033 120000 F      CALL put_crlf
36      ; Convert the ASCII numbers to binary
37      MOV R1,#num1
0036 7900 F      CALL ascbin
38      MOV R1,#num2
0038 120000 F     CALL ascbin
39      MOV R1,#num2
003B 7900 F      CALL ascbin
40      ; Add the 2 numbers, and store the results in SUM
41      ADD a,num1
42      MOV a,num1
43      ADD a,num2
44      MOV sum,a
45      ; Convert SUM from binary to ASCII
46      MOV R1,#sum
47      CALL binasc
48      ; Output sum to console
49      MOV DPT,#sum_mag
50      CALL put_string
51      MOV R1,#sum
52      MOV R2,#4
53      CALL put_data_str
54      JMP start
55      ;
56      DSEG at 8
57      STACK: DS 8      ; At power-up the stack pointer is
58                      ; initialized to point here.
59
60      ;
61      DATA_AREA      segment DATA
62      CONSTANT_AREA segment CODE
63      ;
64      RSEG data_area
65      NUM1: DS 4
66      NUM2: DS 4
67      SUM: DS 4
68      ;
69      RSEG constant_area
70      TYPD_MSG: DB 'TYPE X TO RETYPE A NUMBER',00H

```

Figure 5-1. SAMP1 Listing File (Cont'd.)

```

001B 54595045      71  NUM1_MSG: DB 'TYPE IN FIRST NUMBER: ',00H
001F 20494E20
0023 46495253
0027 54204E55
002B 4D424552
002F 3A20
0031 00
0032 54595045      72  NUM2_MSG: DB 'TYPE IN SECOND NUMBER: ',00H
0036 20494E20
003A 5345434F
003E 4E4204E
0042 554D4245
0046 523A20
0049 00
004A 54484520      73  SUM_MSG: DB 'THE SUM IS ',00H
004E 53554D20
0052 495320
0055 00
74  ;
75  END

```

```

SYMBOL TABLE LISTING
-----
NAME      TYPE      VALUE      ATTRIBUTES
-----
ASCBIN.   .   C ADDR      ---
BINASC.   .   C ADDR      ---
CONSTANT_AREA C SEG      0056H
DATA_AREA .   D SEG      000CH
GET_NUM   .   C ADDR      ---
NUM1_MSG. .   C ADDR      001BH R      SEG=CONSTANT_AREA
NUM1.     .   D ADDR      0000H R      SEG=DATA_AREA
NUM2_MSG. .   C ADDR      0032H R      SEG=CONSTANT_AREA
NUM2.     .   D ADDR      0004H R      SEG=DATA_AREA
PUT_CRLF. .   C ADDR      ---
PUT_DATA_STR. C ADDR      ---
PUT_STRING. C ADDR      ---
SAMPLE.   .   D ADDR      0098H A
SCON.     .   D ADDR      0008H A
STACK.    .   C ADDR      000BH A
START     .   C ADDR      000BH A

```

Figure 5-1. SAMP1 Listing File (Cont'd.)

```

SUM_MSG . . . C ADDR 004AH R SEG-CONSTANT_AREA
SUM . . . D ADDR 008H R SET-DATA_AREA
TH1 . . . D ADDR 008DH A
TMD . . . D ADDR 008H A
TR1 . . . B ADDR 008H.6 A
TYPD_MSG . . . C ADDR 000H R SEG-CONSTANT_AREA

REGISTER BANK(S) USED: 0, TARGET MACHINE(S): 8051
ASSEMBLY COMPLETE, NO ERRORS FOUND

```

Figure 5-1. SAMP1 Listing File (Cont'd.)

```

system-id MCS-51 MACRO ASSEMBLER Vx.v
OBJECT MODULE PLACED IN SAMP2.OBJ
ASSEMBLER INVOKED BY: ASMS1 SAMP2.A51 DEBUG

LOC OBJ      LINE  SOURCE
-----
1      NAME  CONSOLE_IO
2
3      IO_ROUTINES segment CODE
4      RSEG IO_ROUTINES
5      ; This is the console IO routine cluster.
6      PUBLIC put_crlf, put_string, put_data_str, get_num
7      USING 0
8
9      ; This routine outputs a Carriage Return and
10     ; a Line Feed
11     PUT_CRLF:
12     CR EQU 0DH
13     LF EQU 0AH
14     ;
15     MOV A, #cr
16     CALL put_char
17     MOV A, #lf
18     CALL put_char
19     RET
20
21     ; Routine outputs a null-terminated string located
22     ; in CODE memory, whose address is given in DPTR.
23     PUT_STRING:
24     CLR A
25     MOVC A, @A+DPTR
26     JZ  exit
27     CALL put_char
28     INC DPTR
29     JMP  put_string
30     EXIT:
31     RET
32
33     ; Routine outputs a string located in DATA memory,
34     ; whose address is in R1 and its length in R2.
35     PUT_DATA_STR:

```

Figure 5-2. SAMP2 Listing File

```

0016 E7      MOV A, R1
0017 120000   CALL put_char
001A 09      INC R1
001B DAF9    DJNZ R2, put_data_str
001D 22      RET

; Routine outputs a single character to console.
; The character is given in A.
001E 3099FD  PUT_CHAR:
0021 C299    JNB TI, $
0023 F599    CLR TI
0025 22      MOV SBUF, A
0025 22      RET

; Get a 4 character string from console
; and stores it at the address given in R0.
; If a X is received, routine starts over again.
0026 7A04    GET_NUM:
0028 A900    MOV R2, #4 ; set up string length as 4
002A 120000   MOV R1, R0 ; R0 value may be needed for restart
002A 120000   GET_LOOP:
002D C2E7    CALL get_char
002F B41805   ; Next 4 instr's handle X- the routine starts
0032 120000   ; over if received
0035 80EF    CLR ACC.7 ; clear the parity bit
0037 F7      CJNE A, #18H, GO_ON ; if not X- go on
0038 09      CALL put_crlf
0039 DAEF    JMP get_num
003B 22      GO_ON:
0037 F7      MOV R1, A
0038 09      INC R1
0039 DAEF    DJNZ R2, get_loop
003B 22      RET

; Get a single character from console.
; The character is returned in A.
0037 F7      GET_CHAR:
0038 09      INC R1
0039 DAEF    DJNZ R2, get_loop
003B 22      RET

```

Figure 5-2. SAMP2 Listing File (Cont'd.)

```

003C 3098FD      73      JNB RI,$
003F C298        74      CLR RI
0041 ES99        75      MOV A,SBUF
0043 22          76      RET
                          77      ;
                          78      END

SYMBOL TABLE LISTING
-----
NAME      TYPE      VALUE      ATTRIBUTES

ACC.      .      .      D ADDR      00E0H      A
ARG.      .      .      D ADDR      0000H      A
CONSOLE_10 .      .      .      .      .
CR.       .      .      NUMB      000DH      A
EXIT      .      .      C ADDR      0015H      R
GET_CHAR  .      .      C ADDR      003CH      R
GET_LOOP  .      .      C ADDR      002AH      R
GET_NUM   .      .      C ADDR      0026H      R PUB
GO_ON     .      .      C ADDR      0037H      R
IO_ROUTINES. .      .      C SEG      0044H
LF        .      .      NUMB      000AH      A
PUT_CHAR  .      .      C ADDR      001EH      R
PUT_CRLF  .      .      C ADDR      0000H      R PUB
PUT_DATA_STR .      .      C ADDR      0016H      R PUB
PUT_STRING .      .      C ADDR      000BH      R PUB
RI        .      .      B ADDR      0098H.0 A
SBUF      .      .      D ADDR      0099H      A
TI        .      .      B ADDR      0098H.1 A

REGISTER BANK(S) USED: 0, TARGET MACHINE(S): 8051
ASSEMBLY COMPLETE, NO ERRORS FOUND

```

Figure 5-2. SAMP2 Listing File (Cont'd.)

```

MCS-S1 MACRO ASSEMBLER      NUM_CONVERSION
system-id MCS-S1 MACRO ASSEMBLER VxY
OBJECT MODULE PLACED IN SAMP3.OBJ
ASSEMBLER INVOKED BY:  ASMS1 SAMP3.AS1 DEBUG

LOC  OBJ      LINE      SOURCE

1      NAME NUM_CONVERSION
2
3      NUM_ROUTINES segment CODE
4      RSEG NUM_ROUTINES
5      ; This module converts from ASCII to binary
6      ; and back. The binary numbers are signed one-byte
7      ; integers, i.e. range is -128 to +127. Their
8      ; ASCII representation is always 4 char's long-
9      ; i.e. a sign followed by 3 digits.
10     PUBLIC ascbin, binasc
11     USING 0
12     ZERO EQU '0'
13     PLUS EQU '+'
14     MINUS EQU '-'
15
16     ; This routine converts ASCII to binary.
17     ; INPUT- a 4 char string pointed at by R1. The
18     ; number range must be -128 to +127, and the
19     ; string must have 3 digits preceded by a sign.
20     ; OUTPUT- a signed one-byte integer, located where
21     ; the input string started (pointed at by R1).
22     ASCBIN:
23     MOV R0,R1 ; R1 original value needed later
24     ; Compute first digit value, and store it in TEMP
25     TEMP EQU R3
26     INC R0
27     MOV A,@R0
28     CLR C
29     SUBB A,#zero
30     MOV B,#100
31     MUL AB
32     MOV TEMP,A
33     ; Compute the second digit value
34     INC R0

```

Figure 5-3. SAMP3 Listing File





```

002B E7      MOV A,R1          ; Store a plus sign (over-
0029 772B    MOV R1,#plus   ; written by minus if needed)
002B 30E704  JNB sign_on2     ; Test the sign bit
002E 772D    ; Next 3 instructions handle negative numbers
0030 14      MOV R1,#minus   ; Store a minus sign
0031 F4      DEC A
              CPL A
              ; Factor out the first digit
GD_ON2:
81          INC R1
82          MOV B,#100
83          DIV AB
84          ADD A,#zero
85          MOV R1,A         ; store the first digit
86          ; Factor out the second digit
87          INC R1
88          MOV A,B
89          MOV B,#10
90          DIV AB
91          ADD A,#zero
92          MOV R1,A         ; store the second digit
93          ; Store the third digit
94          INC R1
95          MOV A,B
96          MOV B,#10
97          DIV AB
98          ADD A,#zero
99          MOV R1,A         ; store the third digit
          ; note that we return without restoring R1
          RET
100         RET
101         ;
102        END

```

**Figure 5-3. SAMP3 Listing File (Cont'd.)**

## SYMBOL TABLE LISTING

| N A M E                  | T Y P E | V A L U E | A T T R I B U T E S    |
|--------------------------|---------|-----------|------------------------|
| ACC . . . . .            | D ADDR  | 00E0H     | A                      |
| AR1 . . . . .            | D ADDR  | 0001H     | A                      |
| ASCBIN . . . . .         | C ADDR  | 0000H     | R PUB SEG=NUM_ROUTINES |
| B . . . . .              | D ADDR  | 00F0H     | A                      |
| BINASC . . . . .         | C ADDR  | 0028H     | R PUB SEG=NUM_ROUTINES |
| GO_ON2 . . . . .         | C ADDR  | 0032H     | R SEG=NUM_ROUTINES     |
| MINUS . . . . .          | NUMB    | 002DH     | A                      |
| NUM_CONVERSION . . . . . | ---     | ---       | ---                    |
| NUM_ROUTINES . . . . .   | C SEG   | 004BH     | REL=UNIT               |
| PLUS . . . . .           | NUMB    | 002BH     | A                      |
| POS . . . . .            | C ADDR  | 0025H     | R SEG=NUM_ROUTINES     |
| SIGN . . . . .           | B ADDR  | 00E0H.7   | A                      |
| TEMP . . . . .           | REG     | R3        |                        |
| ZERO . . . . .           | NUMB    | 0030H     | A                      |

REGISTER BANK(S) USED: 0, TARGET MACHINE(S): 8051

ASSEMBLY COMPLETE, NO ERRORS FOUND

Figure 5-3. SAMP3 Listing File (Cont'd.)

system-id RL51 mm/dd/yy PAGE 1

system-id MCS-51 RELOCATOR AND LINKER, Vxy, INVOKED BY:

RL51 SAMP1.OBJ,SAMP2.OBJ,SAMP3.OBJ \*

\*\*TO SAMPLE \*

\*\*PRINT (SAMPLE.LST) SYMBOLS LINES PUBLICS IREF

INPUT MODULES INCLUDED

SAMP1.OBJ(SAMPLE)

SAMP2.OBJ(CONSOLE\_ID)

SAMP3.OBJ(NUM\_CONVERSION)

LINK MAP FOR SAMPLE(SAMPLE)

| TYPE | BASE  | LENGTH | RELOCATION | SEGMENT NAME  |
|------|-------|--------|------------|---------------|
| ---- | ----  | ----   | -----      | -----         |
| REG  | 0000H | 0008H  |            | "REG BANK 0"  |
| DATA | 0008H | 0008H  | ABSOLUTE   |               |
| DATA | 0010H | 000CH  | UNIT       | DATA_AREA     |
| CODE | 0000H | 005AH  | ABSOLUTE   |               |
| CODE | 005AH | 0056H  | UNIT       | CONSTANT_AREA |
| CODE | 0080H | 004BH  | UNIT       | NUM_ROUTINES  |
| CODE | 00FBH | 0044H  | UNIT       | IO_ROUTINES   |

SYMBOL TABLE FOR SAMPLE(SAMPLE)

| VALUE   | TYPE    | NAME          |
|---------|---------|---------------|
| ----    | ----    | ----          |
| -----   | MODULE  | SAMPLE        |
| C:005AH | SEGMENT | CONSTANT_AREA |
| D:0010H | SEGMENT | DATA_AREA     |
| C:0075H | SYMBOL  | NUM1_MSG      |
| D:0010H | SYMBOL  | NUM1          |
| C:008CH | SYMBOL  | NUM2_MSG      |
| D:0014H | SYMBOL  | NUM2          |
| D:0098H | SYMBOL  | SCON          |

Figure 5-4. RL51 Output File

```

D:0008H SYMBOL
C:000BH SYMBOL
C:00A4H SYMBOL
D:0018H SYMBOL
D:008DH SYMBOL
D:0089H SYMBOL
B:0088H.6 SYMBOL
C:005AH SYMBOL
-----
D:00E0H MODULE
D:0000H SYMBOL
N:000DH SYMBOL
C:0110H SYMBOL
C:0137H SYMBOL
C:0125H SYMBOL
C:0121H PUBLIC
C:0132H SYMBOL
C:00FBH SEGMENT
N:000AH SYMBOL
C:0119H SYMBOL

system-id RLS1

C:00FBH PUBLIC
C:0111H PUBLIC
C:0106H PUBLIC
B:0098H SYMBOL
D:0099H SYMBOL
B:0098H.1 SYMBOL
-----
D:00E0H MODULE
D:0001H SYMBOL
C:00B0H PUBLIC
D:00F0H SYMBOL
C:00D8H PUBLIC

STACK
START
SUM_MSG
SUM
TH1
TMD
TR1
TYPD_MSG
SAMPLE
CONSOLE_10
ACC
AR0
CR
EXIT
GET_CHAR
GET_LOOP
GET_NUM
GO_ON
IO_ROUTINES
LF
PUT_CHAR

mm/dd/yy PAGE 2

PUT_CRLF
PUT_DATA_STR
PUT_STRING
RI
SBUF
TI
CONSOLE_10
NUM_CONVERSION
ACC
AR1
ASCBIN
B
BINASC

```

Figure 5-4. RL51 Output File (Cont'd.)

```

C:00E2H      SYMBOL      GO_ON2
N:002DH      SYMBOL      MINUS
C:00B0H      SEGMENT     NUM_ROUTINES
N:002BH      SYMBOL      PLUS
C:00D5H      SYMBOL      POS
B:00E0H.7    SYMBOL      SIGN
N:0030H      SYMBOL      ZERO
              SYMBOL      NUM_CONVERSION
              ENDMOD

INTER-MODULE CROSS-REFERENCE LISTING
-----

NAME. . . . . USAGE      MODULE NAMES
-----
ASCBIN. . . . CODE;      NUM_CONVERSION SAMPLE
BINASC. . . . CODE;      NUM_CONVERSION SAMPLE
GET_NUM. . . . CODE;      CONSOLE_IO SAMPLE
PUT_CRLF. . . . CODE;      CONSOLE_IO SAMPLE
PUT_DATA_STR. CODE;      CONSOLE_IO SAMPLE
PUT_STRING. . . CODE;      CONSOLE_IO SAMPLE

```

Figure 5-4. RL51 Output File (Cont'd.)

## Using the Locating Controls

The second example shows how to use the PRECEDE control to specify an order for data segments, in this case because the RL51 algorithm for locating segments results in a segment being left out.

The program is named TEST01. After assembly, the listing of TEST01.OBJ is as shown in figure 5-5. The program's code sequence is irrelevant to the example. The two DATA segments, SEG1 and SEG2, and the BIT segment, BIT3, are the points of interest for this example.

SEG1 is 21H bytes long; SEG2, 50H bytes long; SEG3, one bit long. The assembler listing also shows working register bank 0 (8 bytes long, absolutely located at addresses 00H through 07H).

All these segments are to be located in the on-chip data RAM of an 8051. For the 8051, the directly-addressable on-chip data RAM is 80H bytes long (addresses 00H through 7FH); addresses 20H through 2FH are bit-addressable. The working registers may occupy the first 20H bytes of the space. To see what RL51 does with this program, enter the command

```
RL51 TEST01.OBJ
```

The RL51 listing file is shown in figure 5-6. ERROR 107 informs us that the locate attempt for SEG1 would overflow the data space; SEG1 was ignored (not located) for this reason. The link map shows the following assignments for the remaining segments:

| Addresses     | Segment                          |
|---------------|----------------------------------|
| 00H - 07H     | Register Bank 0                  |
| 08H - 1FH     | GAP                              |
| 20H           | SEG3 (one bit at bit location 0) |
| 20H.1 - 20H.7 | GAP                              |
| 21H - 71H     | SEG2 (50H bytes)                 |

After these segments have been located, there is not enough room for SEG1 (21H bytes). However, there would be enough room if SEG1 were located before the BIT segment. To obtain this result, the command is

```
RL51 TEST01.OBJ PRECEDE(SEG1)
```

The RL51 listing file for this example is shown in figure 5-7. The PRECEDE control caused the link mapping to be as follows:

| Addresses     | Segment                          |
|---------------|----------------------------------|
| 00H - 07H     | Register Bank 0                  |
| 08H - 28H     | SEG1 (21H bytes)                 |
| 29H           | SEG3 (one bit at bit location 0) |
| 29H.1 - 29H.7 | GAP                              |
| 2AH - 7AH     | SEG2 (50H bytes)                 |

Refer to Chapter 2 for details on RL51's allocating algorithm.

## Using RL51 with PL/M-51 Modules

The third example shows how to use RL51 with object modules produced by PL/M-51. The example shows the use of PLM51.LIB and demonstrates PL/M-51 generated segments and the PL/M-51 to ASM51 linkage.

The entire application introduces a way to halt ICE-51 the 8051 In-Circuit Emulator Program, at run time. The procedure CHECK\_EQUAL in the PL/M-51 module CHK\_EQ checks if an arithmetic expression is true. If yes, it calls the HALT\_ICE assembler routine, which causes ICE51 to stop the program that is currently running. The code of the program is irrelevant; the example merely intends to show the program development process.

The PLM51 main module CHK\_EQ is compiled by

```
PLM51 CHKEQ.P51 DEBUG PW(90)
```

The output of the compilation is shown in figure 5-8.

The ASM51 module HLTICE is assembled by

```
ASM51 HLTICE.A51 DEBUG PW(90)
```

The output of the compilation is shown in figure 5-9.

RL51 is invoked by the following command:

```
RL51 CHKEQ.OBJ,HLTICE.OBJ,PLM51.LIB IXREF PW(72)
```

RL51 links the two pre-translated input modules, along with the mandatory library PLM51.LIB. PLM51.LIB must be linked whenever a PL/M-51 module participates in the linkage. The listing files are shown in figures 5-8 and 5-9. The result of the linkage is shown in figure 5-10.

The result of a linkage process that includes PL/M-51 modules deserves an explanation. The following paragraphs describe the modules, segments, and symbols that appear in the output listing of such a linkage. The explanation refers to the actual example (figure 5-10).

In addition to the two input modules CHK\_EQ and HALT\_ICE, RL51 pulled some modules from PLM51.LIB. The two modules ?P0034 and ?P0038 contain common PL/M-51 run-time routines and were pulled to resolve calls to those routines in the CHK\_EQ module. The module ?PIVOR contains the initialization routine (set the stack pointer, set PSW), and is pulled whenever a linkage process encounters a main module written in PL/M-51.

The segments BYTES, BITS, and PROG are the user segments as defined in the ASM51 HALT\_ICE module. The code segments ?P0034S, ?P0038S and ?PIVORS are the code segments of the previously explained run-time routines.

All segments whose names are of the form ?CHK\_EQ?any are segments generated by PL/M-51 as result of compiling module CHK\_EQ. The prefix ?CHK\_EQ? indicates that the segment belongs to the CHK\_EQ module. The suffix indicates the segment type; e.g. PR stands for the PProgram CODE segment, CO for the COnstant CODE segment, DT for DATA segment, and BI for BIT segment.

On-chip segment names may be followed by a register bank number (0-3). This number indicates the register bank that must be in effect while data in this segment is accessed.

The ?STACK segment was discussed before. Note that this segment is not supplied by the user, but is pulled-automatically from PLM51.LIB because the main module is written in PL/M-51. The absolute segment at 0000H-0002H contains the reset vector, which consists of a JUMP to the initialization routine contained in the ?PIVORS segment.



Most of PL/M-51-generated relocatable segments have the UNIT relocation type. A frequent exception is the program code segment (?CHK\_EQ?PR), which is INBLOCK whenever a module is compiled under ROM (MEDIUM), which is the default used by the compiler. Another (less frequent) exception is the BITADDRESSABLE DATA segment generated when bit structures are declared within the PL/M-51 source program.

User symbols appear in the symbol table and the IXREF report. Symbols whose names are equal to segments and modules defined previously represent entry points in the appropriate modules/segments pulled from PLM51.LIB (e.g., the symbol ?P0034 is a code address in the module ?P0034).

Symbols in the format ?*procedure*?BYTE or ?*procedure*?BIT (e.g., ?HALT\_ICE?BYTE) are DATA and BIT addresses used for passing parameters to the appropriate external procedures (as implied by the name). BYTE and WORD parameters are placed at DATA address starting at, for example, ?HALT\_ICE?BYTE. BIT parameters are placed at BIT address starting at ?HALT\_ICE?BIT (see also the *PL/M-51 User's Guide* about PL/M-51 linkage to ASM51).

```

MCS-51 MACRO ASSEMBLER      TEST01
system-id MCS-51 MACRO ASSEMBLER Vxy
OBJECT MODULE PLACED IN TEST01.OBJ
ASSEMBLER INVOKED BY:  ASM51 TEST01.SRC PRINT (:CO:) &
**OBJECT (TEST01.OBJ)

LOC  OBJ      LINE      SOURCE
1          ; This test shows the use of the
2          ; PRECEDE locating control.
3          ; One bit causes failure of the
4          ; RLS1 allocation algorithm,
5          ; but the PRECEDE control fixes it.
6
7          NAME test01
8
9          SEGMENT CODE      prog
10         SEGMENT DATA    seg1
11         SEGMENT DATA    seg2
12         SEGMENT BIT      seg3
13
14         RSEG      prog
15
16         Code segment.
17
18         DB      'CODE IS IRRELEVANT'

0000 434F4445
0004 20495320
0008 49525245
000C 4C455641
0010 4E54

19         RSEG      seg1
20         DS      021H
21
22         RSEG      seg2
23         DS      050H
24
25         RSEG      seg3
26         DBIT     001H
27
28         END
29

```

Figure 5-5. TEST01 Assembly Listing File

system-id RL51

system-id MCS-51 RELOCATOR AND LINKER, Vxy, INVOKED BY:  
RL51 TEST01.OBJ

INPUT MODULES INCLUDED  
TEST01.OBJ(TEST01)

LINK MAP FOR TEST01(TEST01)

| TYPE | BASE    | LENGTH  | RELOCATION | SEGMENT NAME |
|------|---------|---------|------------|--------------|
| REG  | 0000H   | 0008H   |            | "REG BANK 0" |
|      | 0008H   | 0018H   |            | *** GAP ***  |
| BIT  | 0020H   | 0000H.1 | UNIT       | SEG3         |
|      | 0020H.1 | 0000H.7 |            | *** GAP ***  |
| DATA | 0021H   | 0050H   | UNIT       | SEG2         |
| CODE | 0000H   | 0012H   | UNIT       | PRG0         |

IGNORED SEGMENTS  
SEG1

- ERROR 107: ADDRESS SPACE OVERFLOW  
SPACE: DATA  
SEGMENT: SEG1

Figure 5-6. RL51 Listing File without PRECEDE

```

system-id RLS1
system-id MCS-51 RELOCATOR AND LINKER, Vx.y, INVOKED BY:
  RLS1 TEST01.OBJ PRECEDE(SEG1)
INPUT MODULES INCLUDED
  TEST01.OBJ(TEST01)
LINK MAP FOR TEST01(TEST01)

```

| TYPE | BASE    | LENGTH  | RELOCATION | SEGMENT NAME |
|------|---------|---------|------------|--------------|
| ---- | ----    | -----   | -----      | -----        |
| REG  | 0000H   | 0008H   |            | "REG BANK 0" |
| DATA | 0008H   | 0021H   | UNIT       | SEG1         |
| BIT  | 0029H   | 0000H.1 | UNIT       | SEG3         |
|      | 0029H.1 | 0000H.7 |            | *** GAP ***  |
| DATA | 002AH   | 0050H   | UNIT       | SEG2         |
| CODE | 0000H   | 0012H   | UNIT       | PRG          |

Figure 5-7. RLS1 Listing File with PRECEDE

mm/dd/yy PAGE 1

```

PL/M-51 COMPILER      ** ICE51 - Check/Halt **
system-id PL/M-51 Vx.y
COMPILER INVOKED BY: plm51 chkeq.p51 debug pw(90)

$title ('** ICE51 - Check/Halt **')
/.....

/* Check_equal:
/* Check if comparison yields the
/* expected result. If not, call
/* assembler routine to return to ICE.
/.....

:
1 1      chk_eq:
      DO;
2 1      halt_ice:
      PROCEDURE (val1, val2, eq_switch) EXTERNAL;
3 2      DECLARE (val1, val2) WORD, eq_switch BIT; END;

5 1      check_equal:
      PROCEDURE (val1, val2, eq_switch) PUBLIC;
6 2      DECLARE
          (val1, val2) WORD,
          eq_switch BIT;

7 2      IF ((val1 <> val2) <> eq_switch)
          THEN CALL halt_ice (val1, val2, eq_switch);
9 1      END check_equal;

/* dummy main program */

10 1      DECLARE
          p1 WORD CONSTANT (3),
          s1 WORD;

11 1      CALL check_equal(p1*s1, 27/s1, 1);

12 1      END chk_eq;

```

Figure 5-8. PL/M-51 Listing File of CHK\_EQ

```

MODULE INFORMATION:
CODE SIZE
CONSTANT SIZE
DIRECT VARIABLE SIZE
INDIRECT VARIABLE SIZE
BIT SIZE
BIT-ADDRESSABLE SIZE
AUXILIARY VARIABLE SIZE
MAXIMUM STACK SIZE
REGISTER-BANK(S) USED:
34 LINES READ
0 PROGRAM ERROR(S)
END OF PL/M-51 COMPILATION

      (STATIC+OVERLAYABLE)
      87D
      2D
      2D+ 4D
      0D+ 0D
      0D+ 1D
      0D+ 0D
      0D
      6D
      0
      0057H
      0002H
      02H+04H
      00H+00H
      00H+01H
      00H+00H
      0000H
      0006H

```

Figure 5-8. PL/M-51 Listing File of CHK\_EQ (Cont'd.)

```

MCS-51 MACRO ASSEMBLER      '--- ICE51 - Halt ---'      mm/dd/yy      PAGE 1

system-id MCS-51 MACRO ASSEMBLER Vxy
OBJECT MODULE PLACED IN HLTICE.OBJ
ASSEMBLER INVOKED BY: asm51 hltice.asm debug pw(90)

LOC OBJ      LINE      SOURCE

1  $title ('--- ICE51 - Halt ---')
2  ;-----
3  ; Halt_Ice:
4  ; Store word parameters in R45, R67,
5  ; Bit in C and execute A5 instruction
6  ; to return to ICE.
7  ;-----
8  ;
9  NAME      halt_ice
10 PUBLIC  halt_ice, ?halt_ice?bit, ?halt_ice?byte
11 bits      SEGMENT BIT
12 bytes     SEGMENT DATA
13 prog      SEGMENT CODE
14 ;
15 ; RSEG      bits
16 ?halt_ice?bit:
17 bit_par:
18 DBIT 1
19 ;
20 ; RSEG      bytes
21 ?halt_ice?byte:
22 first_par:
23 DS 2
24 second_par:
25 DS 2
26 ;
27 ; RSEG      prog
28 halt_ice:
29 MOV      R4,first_par      ; move 1st par to place
30 MOV      R5,first_par+1
31 MOV      R6,second_par     ; move 2nd par to place

```

Figure 5-9. ASM51 Listing File of HLTICE

```

0006 AF00 F 32 MOV R7,second_par+1 ; move bit par to place
0008 A200 F 34 ;
000A A5 35 DB 0ASH ; illegal op-code.
000B 00 36 NOP ; Will stop ICE-S1 if you
000C 00 37 NOP ; type "GO TIL OPC IS A5"
000D 00 38 NOP ;
000E 22 39 RET ; you can continue after
40 ; stop.
41 END

MCS-51 MACRO ASSEMBLER '... ICES1 - Halt ...'

SYMBOL TABLE LISTING
-----

NAME TYPE VALUE ATTRIBUTES
?HALT_ICE?BIT. B ADDR 0000H.0 R PUB SEG=BITS
?HALT_ICE?BYTE D ADDR 0000H R PUB SEG=BYTES
BIT_PAR. . . B ADDR 0000H.0 R SEG=BITS
BITS. . . B SEG 0001H REL=UNIT
BYTES. . . D SEG 0004H REL=UNIT
FIRST_PAR. . . D ADDR 0000H R SEG=BYTES
HALT_ICE. . . C ADDR 0000H R PUB SEG=PRG
PRG. . . C SEG 000FH REL=UNIT
SECOND_PAR. . . D ADDR 0002H R SEG=BYTES

REGISTER BANK(S) USED: 0, TARGET MACHINE(S): 8051

ASSEMBLY COMPLETE, NO ERRORS FOUND

```

Figure 5-9. ASM51 Listing File of HLTICE (Cont'd.)



mm/dd/yy PAGE 1

system-id RLS1

ISIS-II MCS-51 RELOCATOR AND LINKER, Vxy, INVOKED BY:  
 RLS1 CHKEQ.OBJ,HLTICE.OBJ,PLMS1.LIB IREF PW(72)

INPUT MODULES INCLUDED

CHKEQ.OBJ(CHK\_EQ)  
 HLTICE.OBJ(HALT\_ICE)  
 PLMS1.LIB(?P0034)  
 PLMS1.LIB(?P0038)  
 PLMS1.LIB(?PIV0R)

; LINK MAP FOR CHKEQ(CHK\_EQ)

| TYPE  | BASE    | LENGTH  | RELOCATION | SEGMENT NAME |
|-------|---------|---------|------------|--------------|
| REG   | 0000H   | 0008H   |            | "REG BANK 0" |
| DATA  | 0008H   | 0004H   | UNIT       | BYTES        |
| DATA  | 000CH   | 0004H   | UNIT       | ?CHK_EQ?DT?0 |
| DATA  | 0010H   | 0002H   | UNIT       | ?CHK_EQ?DT   |
|       | 0012H   | 000EH   |            | *** GAP ***  |
| BIT   | 0020H   | 0000H.1 | UNIT       | ?CHK_EQ?BI?0 |
| BIT   | 0020H.1 | 0000H.1 | UNIT       | BITS         |
|       | 0020H.2 | 0000H.6 |            | *** GAP ***  |
| IDATA | 0021H   | 0001H   | UNIT       | ?STACK       |
| CODE  | 0000H   | 0003H   | ABSOLUTE   |              |
| CODE  | 0003H   | 0057H   | INBLOCK    | ?CHK_EQ?PR   |
| CODE  | 005AH   | 0016H   | UNIT       | ?P0038S      |
| CODE  | 0070H   | 000FH   | UNIT       | PRG          |
| CODE  | 007FH   | 000CH   | UNIT       | ?P0034S      |
| CODE  | 008BH   | 0009H   | UNIT       | ?PIV0RS      |
| CODE  | 0094H   | 0002H   | UNIT       | ?CHK_EQ?CO   |

Figure 5-10. RLS1 Listing File of CHK EQ

## SYMBOL TABLE FOR CHECK(CHECK\_EQ)

```

TYPE      VALUE      NAME
----      -
MODULE
C:0003H  CHECK_EQUAL
C:0033H  CHECK_EQ
-----  CHECK_EQUAL
D:000CH  VAL1
D:000EH  VAL2
SMBOL    B:0020H  EQ_SWITCH
SMBOL    C:0003H  CHECK_EQUAL
ENDPRG
C:0094H  PI
D:0010H  SI
C:0033H  1
C:0003H  5
C:0003H  7
C:0003H  8
C:001FH  9
C:0032H

system-id  RLS1

C:0033H  11
C:005AH  12
-----  CHK_EQ

MODULE
B:0020H.1  HALT_ICE?BIT
D:0008H    ?HALT_ICE?BYTE
SMBOL      BIT_PAR
B:0020H.1  BITS
D:0008H    BYTES
D:0008H    FIRST_PAR
C:0070H    HALT_ICE
C:0070H    PRG
D:000AH    SECOND_PAR
-----  HALT_ICE
ENDMOD

```

Figure 5-10. RL51 Listing File of CHK EQ (Cont'd.)

mm/dd/yy PAGE 3

system-id RL51

## INTER-MODULE CROSS-REFERENCE LISTING

```

NAME . . . . . USAGE      MODULE NAMES
-----
?CHECK_EQUAL?BIT . BIT;      CHK_EQ
?CHECK_EQUAL?BYTE . DATA;    CHK_EQ
?HALT_ICE?BIT . . . BIT;      HALT_ICE  CHK_EQ
?HALT_ICE?BYTE . . . DATA;    HALT_ICE  CHK_EQ
?P0034 . . . . . CODE;        ?P0034  CHK_EQ
?P0038 . . . . . CODE;        ?P0038  CHK_EQ
?PIHOR . . . . . CODE;        CHK_EQ  ?PIVOR
?PIVOR . . . . . CODE;        ?PIVOR  CHK_EQ
?PSWOR . . . . . NUMB;        CHK_EQ  ?PIVOR
CHECK_EQUAL . . . . . CODE;    CHK_EQ
HALT_ICE . . . . . CODE;      HALT_ICE  CHK_EQ

```

Figure 5-10. RL51 Listing File of CHK EQ (Cont'd.)

## Introduction

LIB51 allows you to create, modify, and examine library files. It may be executed in interactive or noninteractive mode. In both cases, LIB51 can be invoked directly or by a submit file.

## Invoking LIB51

### Noninteractive Mode

Following is the general syntax for invoking in non-interactive mode:

```
[ directory ] device LIB51 command
```

The librarian will then respond with the sign-on message. It then executes the given command and returns immediately to the host operating system.

### Interactive Mode

Following is the general syntax for invoking LIB51 in interactive mode:

```
[ directory ] device LIB51
```

LIB51 will then respond with its sign-on message. It will then present the prompt (\*), requesting that you enter LIB51 commands. After each command is executed, another prompt will appear as the librarian awaits entry of the next command. This process continues until the EXIT command is entered, thus terminating LIB51.

## Character Set

The LIB51 character set consists of the letters A-Z, the digits 0-9 and the special characters ?, @, and \_.

## LIB51 Commands

Table 6-1 summarizes the LIB51 commands.

## Command Entry

It is often necessary to extend the LIB command to more than one line. Use an ampersand (&) to indicate that you have not entered the complete command and are extending it to another line. The ampersand continuation character may be placed anywhere that a space would normally appear in the command line. That is, the continuation character may be placed before or after commas or parentheses and before or after control words. Any characters that appear on a line to the right of the ampersand and to the left of the carriage return terminating the line are ignored.

Table 6-1. LIB51 Commands

| Command                                                  | Abbreviation | Description                                                            |
|----------------------------------------------------------|--------------|------------------------------------------------------------------------|
| ADD { file[(module[,...])] } [... ] TO library_file      | A            | Adds modules to a library                                              |
| CREATE library_file                                      | C            | Creates a library file                                                 |
| DELETE library_file[(module[,...])]                      | D            | Deletes modules from a library                                         |
| EXIT                                                     | E            | Terminates session with LIB51                                          |
| EXTRACT { file[(module[,...])] } [... ] TO file          | X            | Extracts modules from libraries                                        |
| HELP                                                     | H            | Displays syntax of LIB51 commands                                      |
| LIST { file[(module[,...])] } [... ] [TO file] [PUBLICS] | L [P]        | Lists modules contained in libraries, and optionally lists all publics |
| REPLACE { file[(module[,...])] } [... ] IN library_file  | R            | Replaces modules in a library                                          |

Whenever you enter the continuation character, LIB51 responds by beginning a new line with the continuation prompt—two asterisks (\*\*). LIB51 then waits for you to enter the additional line of input. If you cannot complete the command on the second line, use more ampersands to continue the process until the command is completely entered.

A semicolon may be placed on any command to start a comment. LIB51 will ignore all characters that appear to the right of the semicolon and to the left of the carriage return that terminates the line. If you enter an ampersand to the right of a semicolon, the ampersand will be treated as part of a comment and not as the continuation character.

## Command Descriptions

Following are the descriptions of the LIB51 commands.

### ADD

#### Syntax

```
ADD {file[(module[,...])]}[,...] TO library_file
```

#### Abbreviation

A

#### Description

The ADD command allows you to add the specified files to the library file specified as the destination.

The input filenames may be the names of ordinary object files or object library files. If the input file is an ordinary object file, all modules contained within that file will be added to the designated library. The ordinary object file may have been produced by a translator/assembler, RL51, or the EXTRACT command of LIB51.

If the input file is a library file, it may be specified with or without a list of module names. If you do not specify a list of module names, all of the modules contained in the input library will be added to the destination library. If you do specify the list of module names, only those modules specified in the command are added to the destination library.

The destination library must already exist before the ADD command is entered.

#### Examples

1. `*ADD SIN,COS,TAN TO USER.LIB`

This command adds the three files SIN, COS, and TAN to the destination library USER.LIB.

2. `*ADD LIB.TMP(MOD1,MOD2,MOD3) TO &  
*PROJ.TOM`

This command adds the three modules MOD1, MOD2, and MOD3 of the library LIB.TMP to the destination library PROJ.TOM. Note the use of the ampersand to continue the command.

## CREATE

### Syntax

CREATE *library file*

### Abbreviation

C

### Description

The CREATE command causes an empty library file that has been named in the command to be created. If the file already exists, an error message is issued and the command terminates.

### Examples

1. \*CREATE SLEAZO.LIB

This command creates the empty library file SLEAZO.LIB.

## DELETE

### Syntax

DELETE *library file* ( *module name* [ , . . . ] )

### Abbreviation

D

### Description

The DELETE command removes the specified modules from the designated library file. Modules can be deleted from only one library at a time. If any of the elements specified for deletion cannot be located, a warning is issued.

### Examples

1. \*DELETE SLEAZO.LIB (TRUTH,VALUE)

This command deletes the modules TRUTH and VALUE from the library SLEAZO.LIB.



## EXIT

### Syntax

EXIT

### Abbreviation

E

### Description

In interactive mode, the EXIT command causes LIB51 to terminate—thereby causing control to be returned to the operating system. In noninteractive mode, the EXIT command is ignored.

### Examples

1. \*EXIT

## EXTRACT

### Syntax

EXTRACT {file[(module[,...])]} [,...] TO file

### Abbreviation

X

### Description

The EXTRACT command builds an ordinary object file from the specified files and library members. The extracted files are not deleted; they remain unchanged (i.e., they are nondestructively copied to their destination).

### Examples

1. \*EXTRACT SLEAZO.LIB(WORTH,FREE) TO PROLES.OBJ

The modules WORTH and FREE are nondestructively extracted from SLEAZO.LIB and placed in PROLES.OBJ.

## HELP

### Syntax

HELP

### Abbreviation

H

### Description

The HELP command causes a summary of the syntax of the LIB51 command to appear on the console. Use the HELP command to obtain this information about LIB51 if you require help when entering commands. The following information will appear on the screen:

```
ADD      {file[ (module[,...])]} [,...] TO library_file
CREATE   library_file
DELETE   library_file(module[,...])
EXIT
EXTRACT  {file[(module[,...])]} [,...] TO file
HELP
LIST     {file[(module[,...])]} [,...] [ TO file] [PUBLICS]
REPLACE  {file[(module[,...])]} [,...] IN library_file
```

## LIST

### Syntax

```
LIST {file{ (module[ ,... ] ) } [ ,... ] [ TO file ] [ PUBLICS ]
```

### Abbreviation

```
L [ P ]
```

### Description

The LIST command prints the names of the modules, and, optionally, the names of the public symbols (if you specify PUBLICS) to the specified destination output file. If you do not enter the TO clause, the listing will be directed to the console output. PUBLICS specifies that in addition to the module names, all public symbols contained in those modules will be listed.

### Examples

1. `LIST USER.LIB`

The names of all modules in the library USER.LIB are listed.

2. `LIST USER.LIB(TEMP) PUBLICS`

All public symbols in the module TEMP in the library USER.LIB are listed.

## REPLACE

### Syntax

```
REPLACE {file[ (module[ ,... ] ) ] } [ ,... ] IN library_file
```

### Abbreviation

R

### Description

The REPLACE command allows you to replace object modules in the designated library file with a new version. If a module designated to be replaced does not already exist in the library in an older version, the newer version is simply added to the library.

### Examples

```
1. *REPLACE WORTH,FREE IN SLEAZO.LIB
```

The newer version of WORTH is added to the library SLEAZO.LIB; the new file FREE is also added.

# Summary of RL51 Controls

# A

## Table of Basic Definitions

Table A-1 gives definitions of basic terms used in the command format summary.

Table A-1. Definitions of Common Terms

| Term                | Definition                                                                                                                                                                                     |
|---------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <i>name</i>         | Names can be from 1 to 40 characters long and must be composed of letters A - Z, digits 0 - 9, or special characters (? , @ , _). The first character must be a letter or a special character. |
| <i>module-name</i>  | Same as name.                                                                                                                                                                                  |
| <i>segment-name</i> | Same as name.                                                                                                                                                                                  |
| <i>pathname</i>     | A valid filename reference or device reference. See next two items for examples.                                                                                                               |
| <i>filename</i>     | A reference to a disk file.                                                                                                                                                                    |
| <i>device</i>       | A reference to a non-disk device.<br>Examples: :LP:, :CO:, :TO:                                                                                                                                |
| <i>value</i>        | A 16-bit unsigned integer.<br>Examples: 1011B, 304Q, 4096D (or just 4096), 0C300H                                                                                                              |
| <i>address</i>      | Same as value.                                                                                                                                                                                 |

## RL51 Command Format Summary

Here is a summary of the syntax of the RL51 invocation command. Refer to the Preface for an explanation of the command format notation.

The RL51 command has the overall format

[ *directory|device* ] RL51 *input-list* [ *TO output-file* ] [ *control-list* ]

where

*directory|device* : = ; the directory or device where RL51 resides.

*input-list* : = *input-file* [ *module-list* ] [ , ... ]

*input-file* : = *filename* ; see table A-1

*module-list* : = ( *module-name* [ , ... ] )

*module-name* : = ; see table A-1

*output-file* : = *filename* ; see table A-1

*control-list* : = *control* ...

```

control : = {
    listing-control
    linking-control
    locating-control
    configuration-control
    overlay-control
}

listing-control : = {
    print
    pagewidth
    map
    symbols
    publics
    lines
    ixref
}

print : = { PRINT [(pathname)]
           NOPRINT
}
pathname : = ; see table A-1
pagewidth : = PAGEWIDTH (value)
value : = see table A-1
map : = { MAP
          NMAP
}
symbols : = { SYMBOLS
              NOSYMBOLS
}
publics : = { PUBLICS
              NOPUBLICS
}
lines : = { LINES
            NOLINES
}
ixref : = { IXREF [selection-list]
           NOIXREF
}
selection-list : = (selection-item [, ...])
selection-item : = { generated
                    libraries
}
generated : = { GENERATED
               NOGENERATED
}
libraries : = { LIBRARIES
               NOLIBRARIES
}

linking-control : = { NAME (module-name)
                     debugsymbols
                     debuglines
                     debugpublics
}
debugsymbols : = { DEBUGSYMBOLS
                  NODEBUGSYMBOLS
}
debuglines : = { DEBUGLINES
                NODEBUGLINES
}
debugpublics : = { DEBUGPUBLICS
                  NODEBUGPUBLICS
}

locating-controls : = { PRECEDE
                       DATA
                       BIT
                       IDATA
                       STACK
                       XDATA
                       CODE
} (segment [, ...])

segment : = segment-name [(address)]

```

```

segment-name : * ; see table A-1
address : * ; see table A-1
configuration-control : * ramsize
ramsize : * RAMSIZE (value)
value : * ; see table A-1
overlay-control : * { OVERLAY [ (overlay-unit[ . . . ] ) ]
                     NOOVERLAY
overlay-unit : * ov-module-name calls ov-module-name
ov-module-name : * { module-name }
module-name : * ; see table A-1
calls : * > or ]

```

## Tables of Listing, Linking, Locating, and Overlaying Controls

Tables A-2 through A-6 describe the RL51 controls. Table A-7 gives abbreviations for the controls.

### Notes On Locating Controls

The following notes refer to table A-4.

1. Bit addresses for non-BIT segments in the BIT control must be on byte boundaries; that is, they must be divisible by eight. (BIT-type segments can be aligned on bit boundaries.)
2. The range of addresses for the IDATA control is dependent on the target machine. The 8051 has 128 bytes (addresses 00H -- 7FH). See the RAMSIZE control in this context.
3. The STACK control specifies which segments are to be allocated uppermost in the IDATA space. The memory accessed starts after the highest on-chip RAM address occupied by any previously allocated segment, and continues to the top of the IDATA space.

### NOTE

This control has no other effect on any segments.

The IDATA ?STACK segment, if it exists, is placed higher than segments that were mentioned in the STACK control.

**Table A-2. Listing Controls and Switches**

| Control            | Effect                                                                        |
|--------------------|-------------------------------------------------------------------------------|
| PRINT [(pathname)] | Sends the listing file to the file or device specified by pathname.           |
| NOPRINT            | Suppresses the listing file; overrides any of the following listing controls. |
| PAGewidth (value)  | Specifies the maximum page width to be used.                                  |
| MAP                | Outputs memory map to link summary.                                           |
| NOMAP              | Suppresses memory map.                                                        |
| SYMBOLS            | Outputs local symbols to symbol table.                                        |
| NOSYMBOLS          | Suppresses local symbols.                                                     |



Table A-2. Listing Controls and Switches (Cont'd.)

| Control                           | Effect                                                                       |
|-----------------------------------|------------------------------------------------------------------------------|
| PUBLICS                           | Outputs public symbols to symbol table.                                      |
| NOPUBLICS                         | Suppresses public symbols.                                                   |
| LINES                             | Outputs line numbers to symbol table (high-level language translators only). |
| NOLINES                           | Suppresses line numbers.                                                     |
| IXREF [( <i>selection-list</i> )] | Appends intermodule cross-reference report to print file.                    |
| NOIXREF                           | Suppresses the intermodule cross-reference report.                           |

NOTE: The default for any control (except IXREF) is the positive form (PRINT, MAP, SYMBOLS, PUBLICS, and LINES).

Table A-3. Linking Controls and Switches

| Control                     | Effect                                                                                                                                                    |
|-----------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------|
| NAME ( <i>module-name</i> ) | Specifies the name of the output module. If the NAME control is omitted, the output module name defaults to the name of the first input module processed. |
| DEBUGSYMBOLS                | Copies local symbol information to output file.                                                                                                           |
| NODEBUGSYMBOLS              | Suppresses local symbols.                                                                                                                                 |
| DEBUGPUBLICS                | Copies public symbol information to output file.                                                                                                          |
| NODEBUGPUBLICS              | Suppresses public symbols.                                                                                                                                |
| DEBUGLINES                  | Copies line number information (high-level language translators only) to output file.                                                                     |
| NODEBUGLINES                | Suppresses line numbers.                                                                                                                                  |

NOTE: For all linking controls except NAME, the default is the positive form (DEBUGSYMBOLS, DEBUGPUBLICS, and DEBUGLINES).

Table A-4. Locating Controls

| Control | Address Space                                                | Address Range (Hex)      | Segment Types (and Attributes) |
|---------|--------------------------------------------------------------|--------------------------|--------------------------------|
| PRECEDE | Register banks and bit-addressable space in on-chip data RAM | 00H-2FH                  | DATA (UNIT-aligned); IDATA     |
| BIT     | Bit-addressable space in on-chip data RAM                    | 00H - 7FH (see note 1)   | BIT; DATA; IDATA               |
| DATA    | Directly-addressable on-chip data RAM                        | 00H - 7FH                | DATA (UNIT-aligned); IDATA     |
| IDATA   | Indirectly-addressable on-chip data RAM                      | 00H - 0FFFH (see note 2) | IDATA                          |
| STACK   | Same as IDATA (see note 3)                                   | Same as IDATA            | Same as IDATA                  |
| XDATA   | External data RAM                                            | 0 - 0FFFFH               | XDATA                          |
| CODE    | Code memory                                                  | 0 - 0FFFFH               | CODE                           |

Table A-5. Configuration Control

| Control                  | Effect                                                      |
|--------------------------|-------------------------------------------------------------|
| RAMSIZE ( <i>value</i> ) | Specifies the amount of on-chip RAM the object is aimed to. |

Table A-6. Overlay Controls

| Control                          | Effect                                                                                                |
|----------------------------------|-------------------------------------------------------------------------------------------------------|
| OVERLAY ( <i>overlay-units</i> ) | Overlays data segments, based on the information in the module declarations and in the overlay units. |
| NOOVERLAY                        | Suppresses the overlaying of data segments.                                                           |

Table A-7. Abbreviations for Command Words

| Command Word   | Abbreviation |
|----------------|--------------|
| BIT            | BI           |
| CODE           | CO           |
| DATA           | DT           |
| DEBUGLINES     | DL           |
| DEBUGPUBLICS   | DP           |
| DEBUGSYMBOLS   | DS           |
| GENERATED      | GN           |
| IDATA          | ID           |
| IXREF          | IX           |
| LIBRARIES      | LB           |
| LINES          | LI           |
| MAP            | MA           |
| NAME           | NA           |
| NODEBUGLINES   | NODL         |
| NODEBUGPUBLICS | NODP         |
| NODEBUGSYMBOLS | NODS         |
| NOGENERATED    | NOGN         |
| NOIXREF        | NOIX         |
| NOLIBRARIES    | NOLB         |
| NOLINES        | NOLI         |
| NOMAP          | NOMA         |
| NOOVERLAY      | NOOL         |
| NOPRINT        | NOPR         |
| NOPUBLICS      | NOPL         |
| NOSYMBOLS      | NOSB         |
| OVERLAY        | OL           |
| PAGEWIDTH      | PW           |
| PRECEDE        | PC           |
| PRINT          | PR           |
| PUBLICS        | PL           |
| RAMSIZE        | RS           |
| STACK          | ST           |
| SYMBOLS        | SB           |
| TO             | TO           |
| XDATA          | XD           |

# RL51 Error Messages

# B

RL51 error messages describe warnings, errors, and fatal errors. A warning is a detected condition that may or may not be what the user desired; a warning does not terminate the link/locate operation. An error does not terminate operation, but probably results in an output module that cannot be used. A fatal error terminates operation of RL51.

This appendix lists the warning, error, and fatal error messages in that order. The text of each message is in UPPER CASE. A brief explanation of the probable cause for the error condition accompanies each error message.

## Warnings

### WARNING 1: UNRESOLVED EXTERNAL SYMBOL

SYMBOL: *external-name*  
MODULE: *file-name(module-name)*

The specified external symbol, requested in the specified module, has no matching public symbol in any of the input modules.

### WARNING 2: REFERENCE MADE TO UNRESOLVED EXTERNAL

SYMBOL: *external-name*  
MODULE: *file-name(module-name)*  
REFERENCE: *code-address*

The specified unresolved external is referenced in the specified module at the specified code address.

### WARNING 3: ASSIGNED ADDRESS NOT COMPATIBLE WITH ALIGNMENT

SEGMENT: *segment-name*

The address specified for the segment in a locating control is not compatible with the segment's alignment. The segment is placed at the specified address, violating its alignment.

### WARNING 4: DATA SPACE MEMORY OVERLAP

FROM: *byte.bit address*  
TO: *byte.bit address*

The data space in the given range is occupied by two or more segments.

### WARNING 5: CODE SPACE MEMORY OVERLAP

FROM: *byte address*  
TO: *byte address*

The code space in a given range is occupied by two or more segments.

### WARNING 6: XDATA SPACE MEMORY OVERLAP

FROM: *byte address*  
TO: *byte address*

The xdata space in the given range is occupied by two or more segments.

**WARNING 7: MODULE NAME NOT UNIQUE**  
**MODULE:** *file-name(module-name)*

The specified name was used as the module name for more than one module. The specified module is not processed.

**WARNING 8: MODULE NAME EXPLICITLY REQUESTED FROM ANOTHER FILE**  
**MODULE:** *file-name(module-name)*

The specified module was requested, explicitly, to be processed from another file that has not yet been processed. The specified module is not processed.

**WARNING 9: EMPTY ABSOLUTE SEGMENT**  
**MODULE:** *file-name(module-name)*

The specified module contains an empty absolute segment. This segment is not allocated. The base address of this segment may be overlapped without any additional message.

## **Errors**

**ERROR 101: SEGMENT COMBINATION ERROR**  
**SEGMENT:** *segment-name*  
**MODULE:** *file-name(module-name)*

The attributes of the specified partial segment, in the specified module, contradict those of previous (unspecified) occurrences of partial segments with the same name. The segment is ignored.

**ERROR 102: EXTERNALS ATTRIBUTE MISMATCH**  
**SYMBOL:** *external-name*  
**MODULE:** *file-name(module-name)*

The attributes of the specified external symbol, in the specified module, contradict those of previous (unspecified) occurrences of public symbol with the same name. The specified symbol is ignored.

**ERROR 103: EXTERNAL ATTRIBUTES DO NOT MATCH PUBLIC**  
**SYMBOL:** *symbol-name*  
**MODULE:** *file-name(module-name)*

The attributes of the specified external (public) symbol, in the specified module, contradict those of previous (unspecified) occurrences of public (external) symbol with the same name. The specified symbol is ignored.

**ERROR 104: MULTIPLE PUBLIC DEFINITIONS**  
**SYMBOL:** *symbol-name*  
**MODULE:** *file-name(module-name)*

The specified public symbol, in the specified module, has already been defined in a previously (unspecified) processed module. The specified symbol is ignored.

**ERROR 105: PUBLIC REFERS TO IGNORED SEGMENT**

SYMBOL: *public-name*  
SEGMENT: *segment-name*

The specified public symbol is defined referencing the specified ignored segment. The specified public symbol is ignored.

**ERROR 106: SEGMENT OVERFLOW**

SEGMENT: *segment-name*

The specified segment, after combination, is larger than the maximum segment size allowed for the segment according to its type or to the given locating control. The specified segment is ignored.

**ERROR 107: ADDRESS SPACE OVERFLOW**

SPACE: *space-name*  
SEGMENT: *segment name*

RL51 was unable to allocate the specified relocatable segment, according to the segment relocation type, in the specified address space. The specified segment is ignored.

**ERROR 108: SEGMENT IN LOCATING CONTROL CANNOT BE ALLOCATED**

SEGMENT: *segment name*

RL51 was unable to allocate the specified relocatable segment that appears in the locating control, according to the requirements imposed by the locating control and according to the segment relocation type. The specified segment is ignored.

**ERROR 109: EMPTY RELOCATABLE SEGMENT**

SEGMENT: *segment-name*

The specified segment, after combination has zero size. The specified segment is ignored.

**ERROR 110: CANNOT FIND SEGMENT**

SEGMENT: *segment-name*

The specified segment name occurred in the command tail but is not the name of any segment defined within the input files. The specified segment is ignored.

**ERROR 111: SPECIFIED BIT ADDRESS NOT ON BYTE BOUNDARY**

SEGMENT: *segment-name*

The specified segment was requested in a BIT locating control. The segment is not a BIT segment, and the requested address is not on byte boundary. The specified segment is ignored.

**ERROR 112: SEGMENT TYPE NOT LEGAL FOR COMMAND**

SEGMENT: *segment-name*

The specified segment is not one of the types that are legal for the locating control for which it is specified. The specified segment is ignored.

**ERROR 113: RESERVED.**

ERROR 121: IMPROPER FIXUP  
MODULE: *file-name(module-name)*  
SEGMENT: *segment-name*  
OFFSET: *pseg-offset*

An error occurred in the evaluation of a fixup. An example of this error is when the value of the fixup expression does not meet the requirements of the type of the referenced location. A fixup is an address that cannot be determined at compile/assembly-time. It is marked as relocatable, and at RL-51 time is assigned an address. A fixup is the address assigned to that relocatable symbol.

FATAL ERROR 208: INVALID FILE NAME  
*partial command*

The file-name specified in the command is not a valid file name. The command is repeated up to and including the point of error.

FATAL ERROR 209: FILE USED IN CONFLICTING CONTEXTS  
FILE: *file-name*

The specified file is used in more than one context, for example, using the same file for both input and output. (This may be caused by specifying for the first input file a file that has no extension, and not specifying an output file.)

FATAL ERROR 210: I/O ERROR, INPUT FILE;  
UDI ERROR: EXCEPTION <num>: <ext>  
FILE: *file-name*

An I/O error was detected in accessing an input file. The text of the message includes a description of the specific I/O error that occurred. See the user's guide for your operating system for a list of possible I/O errors.

FATAL ERROR 211: I/O ERROR, OUTPUT FILE; ERROR #  
FILE: *file-name*

An I/O error was detected in accessing the output file. The text of the message includes a description of the specific I/O error that occurred. See the user's guide for your operating system for a list of possible I/O errors.

FATAL ERROR 212: I/O ERROR, LISTING FILE; ERROR #  
FILE: *file-name*

An I/O error was detected in accessing the listing file. The text of the message includes a description of the specific I/O error that occurred. See the user's guide for your operating system for a list of possible I/O errors.

FATAL ERROR 213: I/O ERROR, TEMPORARY FILE; ERROR #  
FILE: *file-name*

An I/O error was detected in accessing a temporary file. The text of the message includes a description of the specific I/O error that occurred. See the user's guide for your operating system for a list of possible I/O errors.

FATAL ERROR 214: INPUT PHASE ERROR  
MODULE: *file-name(module-name)*

This error occurs when RL51 encounters different data during pass two than it read during pass one.

FATAL ERROR 215: CHECK SUM ERROR  
MODULE: *file-name(module-name)*

A bad check sum was detected in the input module. This indicates a bad input module or a read error.

FATAL ERROR 216: INSUFFICIENT MEMORY

The memory available for execution of RL51 has been used up. This is usually caused by too many external /public symbols or segments in the input files or by too many errors.

FATAL ERROR 217: NO MODULE TO BE PROCESSED

After scanning all the input files, no module was selected to be processed. This is usually caused by an empty input file(s) or incorrect module names in the input list.

FATAL ERROR 218: NOT AN OBJECT FILE  
FILE: *file-name*

The file named in the message, judging by its first byte of data, is not a valid object file.

FATAL ERROR 219: NOT AN 8051 OBJECT FILE  
FILE: *file-name*

The translator-ID field in the module header record indicates that the specified module is not an 8051 object module.

FATAL ERROR 220: INVALID INPUT MODULE  
MODULE: *file-name(module-name)*

The specified input module was found to be invalid. Possible causes are incorrect record order, incorrect record type, illegal field, illegal relation between fields, or a missing required record. This error could be the result of a translator record.

FATAL ERROR 221: MODULE SPECIFIED MORE THAN ONCE  
*partial command*

The input list in the invocation line contains the same module name more than once. The command is repeated up to and including the point of error.

FATAL ERROR 222: SEGMENT SPECIFIED MORE THAN ONCE  
*partial command*

The locating controls in the invocation line contain the same segment name more than once. The command is repeated up to and including the point of error.

FATAL ERROR 224: DUPLICATE KEYWORD  
*partial command*

The same keyword appears in the command more than once. The command is repeated up to and including the point of error.

FATAL ERROR 225: SEGMENT ADDRESSES ARE NOT IN  
ASCENDING ORDER

*partial command*

The addresses of the segments within one locating control are not in ascending order. The command is repeated up to and including the point of error.

FATAL ERROR 226: SEGMENT ADDRESS INVALID FOR CONTROL  
*partial command*

The address requested for a segment is not valid for the given locating control. The command is repeated up to and including the point of error.

FATAL ERROR 227: PAGEWIDTH PARAMETER OUT OF RANGE  
*partial command*

The PAGEWIDTH parameter given is out of the acceptable range.

FATAL ERROR 228: RAMSIZE PARAMETER OUT OF RANGE  
*partial command*

The RAMSIZE parameter given is out of acceptable range.

FATAL ERROR 229: I/O ERROR, OVERLAY FILE; ERROR#  
FILE: *file-name*

An I/O error was detected in accessing an overlay file. The text of the message includes a description of the specific I/O error that occurred. See the user's guide for your operating system for a list of possible I/O errors. (This error occurs only if IXREF was requested. Its occurrence does not invalidate the output object file.)

FATAL ERROR 230: INCOMPATIBLE OVERLAY VERSION  
FILE: *file-name*

The overlay file, although loaded successfully, has a version number that is not the one expected by RL51. The possible cause is that the RL51 program and the loaded overlay are not of the same version. (This error occurs only if IXREF or OVERLAY was requested. If only IXREF was requested, the output object file is valid.)

FATAL ERROR 231: TOO MANY IXREF ENTRIES

The number of IXREF entries (entry is a pair consisting of modules and symbol reference) is too large to be processed. The IXREF listing step is not performed. The NOLIBRARIES and NOGENERATED controls may be used in order to decrease this number and overcome the error. (This error occurs only if IXREF was requested. Its occurrence does not invalidate the output object file.)

FATAL ERROR 232: OVERLAY CONTROL CONFLICTS XREF  
SELECTOR ITEMS

The overlay control should not appear with the IXREF selector items NOLIBRARIES or NOGENERATED.

FATAL ERROR 233: ILLEGAL USE OF \* IN OVERLAY  
CONTROL



The use of \* > \* or \* J \* with the OVERLAY control is illegal.

FATAL ERROR 240: INTERNAL PROCESS ERROR

RL51 has detected that it has made a processing error. This error indicates a bug within RL51.

# LIB51 Command Summary

# C

Table C-1. LIB51 Commands

| Command                                                  | Abbreviation | Description                                                            |
|----------------------------------------------------------|--------------|------------------------------------------------------------------------|
| ADD { file[(module[,...])] } [... ] TO library_file      | A            | Adds modules to a library                                              |
| CREATE library_file                                      | C            | Creates a library file                                                 |
| DELETE library_file(module[,...])                        | D            | Deletes modules from a library                                         |
| EXIT                                                     | E            | Terminates session with LIB51                                          |
| EXTRACT { file[(module[,...])] } [... ] TO file          | X            | Extracts modules from libraries                                        |
| HELP                                                     | H            | Displays syntax of LIB96 commands                                      |
| LIST { file[(module[,...])] } [... ] [TO file] [PUBLICS] | L [P]        | Lists modules contained in libraries, and optionally lists all publics |
| REPLACE { file[(module[,...])] } [... ] IN library_file  | R            | Replaces modules in a library                                          |

# LIB51 Error Messages

# D

## INSUFFICIENT MEMORY

LIB51 cannot execute the command because it requires more memory than the amount of memory available in the system.

## INVALID SYNTAX

The command was not entered properly. Reenter it using the correct syntax.

## UNRECOGNIZED COMMAND

An illegal or misspelled command was entered. The only commands are ADD, CREATE, DELETE, EXIT, EXTRACT, HELP, LIST, REPLACE, and their respective abbreviations.

## INVALID MODULE NAME

The specified module name contains an invalid character or starts with a digit.

## MODULE NAME TOO LONG

The specified module name exceeds 40 characters.

## RIGHT PARENTHESIS EXPECTED

A ")" is missing in the command.

## *pathname*, CHECKSUM ERROR

The specified file has an error in one of its checksum fields. This is usually the result of an I/O error.

## *pathname*, ILLEGAL RECORD FORMAT

This error is usually caused by an I/O error or a translation error.

## *pathname*, BAD RECORD SEQUENCE

This error is usually caused by an I/O error or a translation error.

## *pathname*, DUPLICATE SYMBOL IN INPUT

You have attempted to ADD or REPLACE a module that contains a public symbol that is already within the library.

## *pathname*, ATTEMPT TO ADD DUPLICATE MODULE

The specified module name already appears within the library.

## *pathname*, FILE ALREADY EXISTS

The specified file in the CREATE command already exists. Choose another name for the library.

*pathname*, NOT LIBRARY

The specified file is not a library.

The TO filename is omitted in the ADD command.

UNRECOGNIZED COMMAND

An illegal or misspelled command was entered. The only legal commands are ADD, CREATE, DELETE, LIST, and EXIT.

## File or Module Errors

The following errors indicate that there is some problem with the file or module specified. There is no partial copy of the command given with these error messages.

FILE ALREADY EXISTS

The file specified in the CREATE command already exists. Choose a new name for the library.

*filename*, DUPLICATE SYMBOL IN INPUT

You have attempted to add a file that contains a PUBLIC symbol already within the library.

*filename*, NOT LIBRARY

The specified file is not a library.

*filename(modname)*: NOT FOUND

You have attempted to delete a module that does not exist. Check for misspelling of the filename or module name.

*modname*—ATTEMPT TO ADD DUPLICATE MODULE

The specified module name already appears within the library.

*symbol*—ALREADY IN LIBRARY

You have attempted to add a module that contains a PUBLIC symbol that is already in the library.

*filename*, CHECKSUM ERROR

*filename*, OBJECT RECORD TOO SHORT

*filename*, ILLEGAL RECORD FORMAT

LIB51 cannot process the specified file because it is not a legal object file. Possible cause is a file damage or translator error.

# Hexadecimal-Decimal Conversion Table

# E

Table E-1 is for hexadecimal to decimal and decimal to hexadecimal conversion. To find the decimal equivalent of a hexadecimal number, locate the hexadecimal number in the correct position and note the decimal equivalent. Add the decimal numbers.

To find the hexadecimal equivalent of a decimal number, locate the next lower decimal number in the table and note the hexadecimal number and its position. Subtract the decimal number shown in the table from the starting number. Find the difference in the table. Continue this process until there is no difference.

Table E-1. Hexadecimal-Decimal Conversion Table

| Most Significant Byte |        |         |       | Least Significant Byte |     |         |     |
|-----------------------|--------|---------|-------|------------------------|-----|---------|-----|
| Digit 4               |        | Digit 3 |       | Digit 2                |     | Digit 1 |     |
| HEX                   | DEC    | HEX     | DEC   | HEX                    | DEC | HEX     | DEC |
| 0                     | 0      | 0       | 0     | 0                      | 0   | 0       | 0   |
| 1                     | 4 096  | 1       | 256   | 1                      | 16  | 1       | 1   |
| 2                     | 8 192  | 2       | 512   | 2                      | 32  | 2       | 2   |
| 3                     | 12 288 | 3       | 768   | 3                      | 48  | 3       | 3   |
| 4                     | 16 384 | 4       | 1 024 | 4                      | 64  | 4       | 4   |
| 5                     | 20 480 | 5       | 1 280 | 5                      | 80  | 5       | 5   |
| 6                     | 24 576 | 6       | 1 536 | 6                      | 96  | 6       | 6   |
| 7                     | 28 672 | 7       | 1 792 | 7                      | 112 | 7       | 7   |
| 8                     | 32 768 | 8       | 2 048 | 8                      | 128 | 8       | 8   |
| 9                     | 36 864 | 9       | 2 304 | 9                      | 144 | 9       | 9   |
| A                     | 40 960 | A       | 2 560 | A                      | 160 | A       | 10  |
| B                     | 45 056 | B       | 2 816 | B                      | 176 | B       | 11  |
| C                     | 49 152 | C       | 3 072 | C                      | 192 | C       | 12  |
| D                     | 53 248 | D       | 3 328 | D                      | 208 | D       | 13  |
| E                     | 57 344 | E       | 3 584 | E                      | 224 | E       | 14  |
| F                     | 61 440 | F       | 3 840 | F                      | 240 | F       | 15  |

abbreviations, 3-14, A-5  
 absolute object file, 4-5  
 absolute object module, 1-2  
 absolute segments, 2-2  
 ADD, 6-2  
 address, 3-2  
 address spaces, 2-3, 2-4  
 allocation, 3-8  
 allocation process, 2-3  
 assembler (ASM51), 1-3, 5-1  
  
 BIT, 2-2, 2-3, 2-4, 3-9  
 BITADDRESSABLE, 2-2, 2-3  
 BLOCK, 2-2  
  
 CODE, 2-2, 2-3, 3-9  
 command entry, 3-1  
 command, invocation,  
     *see* invocation command  
 comments, 3-2  
 configuration controls, 3-11  
 console display, 4-1  
 continuation lines, 3-2  
 control-list, 3-1  
 controls, 3-4  
     *see also* linking controls, listing controls,  
     locating controls  
 CREATE, 6-4  
  
 DATA, 2-2, 2-3, 3-9  
 DEBUG control, 1-3, 3-4  
 debugging, 1-1  
 DEBUGLINES, 3-7  
 DEBUGPUBLICS, 3-7  
 DEBUGSYMBOLS, 3-7  
 DELETE, 6-5  
 development process, 1-1, 1-2  
 device, 3-2  
  
 editor, text, 1-3  
 error messages, 4-4, B-1, D-1  
 EXIT, 6-6  
 external references, 2-4  
  
 filename, 3-2  
  
 hexadecimal-decimal conversion, E-1  
  
 ICE-51 in-circuit emulator, 1-3  
 IDATA, 2-2, 2-3, 3-9  
 in-circuit emulator,  
     *see* ICE-51 in-circuit emulator  
 INPAGE, 2-2  
 input-list, 3-1, 3-2  
 invocation command, 3-2, 6-1  
     address, 3-2  
     control-list, 3-1  
     device, 3-2  
     filename, 3-2

input-list, 3-1, 3-2  
 module-name, 3-2  
 name, 3-2  
 output-file, 3-3  
 pathname, 3-2  
 segment-name, 3-2  
 IXREF, 4-4, 4-5  
  
 LIB51, 6-1  
     error messages, D-1, D-2  
 LINES, 3-5, 3-6, 3-15  
 linking controls, 3-8, A-3  
     NAME, 3-7  
 linking switches, 3-7  
     DEBUGLINES, 3-7, 3-8  
     DEBUGPUBLICS, 3-7, 3-8  
     DEBUGSYMBOLS, 3-7, 3-8  
     NODEBUGLINES, 3-8  
     NODEBUGPUBLICS, 3-8  
     NODEBUGSYMBOLS, 3-8  
 link summary, 4-1  
 LIST, 6-9  
 listing controls, 3-4, A-3  
     DEBUG control, 3-7  
     listing file, 3-4  
 listing file, 4-1  
 listing switches, 3-6  
     IXREF, 4-4, 4-5  
     LINES, 3-5, 3-6  
     MAP, 3-5, 3-6  
     NOLINES, 3-6  
     NOMAP, 3-6  
     NOPUBLICS, 3-6  
     NOSYMBOLS, 3-6  
     PUBLICS, 3-5, 3-6  
     SYMBOLS, 3-5, 3-6  
 locating controls, 3-8, 3-9, 5-16, A-4  
     BIT, 3-9  
     CODE, 3-9  
     DATA, 3-9  
     IDATA, 3-9  
     PRECEDE, 3-9, 5-16  
     STACK, 3-9  
     XDATA, 3-9  
  
 major functions, 2-1  
 MAP, 3-5, 3-6  
 memory map, 3-4  
 modifying, 1-1  
 module, 1-2, 2-1  
 modular programming, 1-1  
 module-name, 3-2  
  
 NAME, 3-7  
     name, 3-2  
 NODEBUGLINES, 3-8  
 NODEBUGPUBLICS, 3-8  
 NODEBUGSYMBOLS, 3-8  
 NOIXREF, 3-6

NOLINES, 3-6  
NOMAP, 3-6  
NOOVERLAY, 3-11, 3-12  
NOPRINT, 3-5  
NOPUBLICS, 3-6  
NOSYMBOLS, 3-6  
notation, A-1  
  
output-file, 3-3  
OVERLAY, 3-11, 3-12  
  
PAGE, 2-2, 2-3  
partial segments, 2-2  
pathname, 3-2  
PRECEDE, 3-9, 5-16  
PRINT, 3-4  
program, 1-2  
program development, 1-1, 1-2  
PROM programmer, 1-1  
PUBLICS, 3-5, 3-6  
  
RAMSIZE, 3-11  
relocatable segments, 2-2, 2-3  
relocation, 1-3, 2-2  
RL51, 1-2, 2-1, 2-2, 3-1, 5-1  
    command format, A-1  
    controls, 3-4, A-3  
    error messages, B-1  
    pass, 2-2  
  
segment, 1-2, 2-2  
segment-name, 3-2  
segment type, absolute, 2-2  
segment type, relocatable, 2-2, 2-3  
STACK, 2-2, 2-3  
SYMBOLS, 3-5, 3-6  
symbol table, 4-3  
  
UNIT, 2-2, 2-3  
  
XDATA, 2-2, 2-3, 3-9